

MJ 10007	Mot	Si-N-Darl+Di	=MJ 10003: + integr. Speedup-Diode	23a	TO-3	-	-	-
MJ 10008	Mot	Si-N-Darl+Di	SMPS, 650/450V, 20A, 175W, +Speedup-Diode	23a	TO-3	-	-	-
MJ 10009	Mot	Si-N-Darl+Di	=MJ 10008: 700/500V	23a	TO-3	-	-	-
MJ 10011	Mot	Si-N-Darl+Di	S P, -/1400V, 8A, 80W	23a	TO-3	-	-	-
MJ 10012	Mot	Si-N-Darl+Di	S P, 600/400V, 10A, 175W, hFE>100	23a	TO-3	-	-	BUW 81(A), 2SD685
MJ 10013	Mot	Si-N-Darl+Di	SMPS, 650/550V, 10A, 175W, +Speedup-Diode	23a	TO-3	-	-	-
MJ 10014	Mot	Si-N-Darl+Di	=MJ 10013: 700/600V	23a	TO-3	-	-	-
MJ 10015	Mot	Si-N-Darl+Di	SMPS, 600/400V, 50A, 250W, +Speedup-Diode	23a	TO-3	-	-	-
MJ 10016	Mot	Si-N-Darl+Di	=MJ 10015: 700/500V	23a	TO-3	-	-	-
MJ 10020	Mot	Si-N-Darl+Di	SMPS, 300/200V, 60A, 250W, +Speedup-Diode	23a	TO-3	-	-	-
MJ 10021	Mot	Si-N-Darl+Di	=MJ 10020: 350/250V	23a	TO-3	-	-	-
MJ 10022	Mot	Si-N-Darl+Di	SMPS, 450/350V, 40A, 250W, +Speedup-Diode	23a	TO-3	-	-	-
MJ 10023	Mot	Si-N-Darl+Di	=MJ 10022: 600/400V	23a	TO-3	-	-	-
MJ 10024	Mot	Si-N-Darl+Di	SMPS, 1000/750V, 20A, 250W, +Speedup-Diode	23a	TO-3	-	-	-
MJ 10025	Mot	Si-N-Darl+Di	=MJ 10024: 1200/850V	23a	TO-3	-	-	-
MJ 10041	Mot	Si-N-Darl+Di	=MJ 10042: + integr. Speedup-Diode	-	-	-	-	-
MJ 10042	Mot	Si-N-Darl+Di	S P, 900/850V, 37.5A, 250W, hFE>35	-	-	-	-	-
MJ 10044	Mot	Si-N-Darl+Di	=MJ 10045: + integr. Speedup-Diode	-	-	-	-	-
MJ 10045	Mot	Si-N-Darl+Di	S P, 500/450V, 75A, 250W, hFE>50	-	-	-	-	-
MJ 10047	Mot	Si-N-Darl+Di	=MJ 10048: + integr. Speedup-Diode	-	-	-	-	-
MJ 10048	Mot	Si-N-Darl+Di	S P, 300/250V, 100A, 250W, hFE>75	-	-	-	-	-
MJ 10050	Mot	Si-N-Darl+Di	S P, 900/850V, 75A, 500W	-	-	-	-	-
MJ 10051	Mot	Si-N-Darl+Di	S P, 900/850V, 75A, 500W, + Speedup-D.	-	-	-	-	-
MJ 10052	Mot	Si-N-Darl+Di	=MJ 10051: 900/750V	-	-	-	-	-
MJ 10100	Mot	Si-N-Darl+Di	S P, 500/450V, 150A, 500W	-	-	-	-	-
MJ 10101	Mot	Si-N-Darl+Di	S P, 500/450V, 150A, 500W, +Speedup-D.	-	-	-	-	-
MJ 10102	Mot	Si-N-Darl+Di	=MJ 10101: 500/350V	-	-	-	-	-
MJ 10200	Mot	Si-N-Darl+Di	S P, 300/250V, 300A, 500W	-	-	-	-	-
MJ 10201	Mot	Si-N-Darl+Di	S P, 300/250V, 300A, 500W, +Speedup-D.	-	-	-	-	-
MJ 10202	Mot	Si-N-Darl+Di	=MJ 10201: 300/200V	-	-	-	-	-
MJ 11011	Mot,Sgs	Si-P-Darl+Di	S P, 60V, 30A, 200W, hFE>1000	23a	TO-3	-	-	BDX 68A...C
MJ 11012	Mot,Sgs	Si-N-Darl+Di	S P, 60V, 30A, 200W, hFE>1000	23a	TO-3	-	-	BDX 69A...C
MJ 11013	Mot,Sgs	Si-P-Darl+Di	=MJ 11011: 90V	23a	TO-3	-	-	BDX 68B...C
MJ 11014	Mot,Sgs	Si-N-Darl+Di	=MJ 11012: 90V	23a	TO-3	-	-	BDX 69B...C
MJ 11015	Mot,Sgs	Si-P-Darl+Di	=MJ 11011: 120V	23a	TO-3	-	-	BDX 68C
MJ 11016	Mot,Sgs	Si-N-Darl+Di	=MJ 11012: 120V	23a	TO-3	-	-	BDX 69C
MJ 11017	Mot	Si-P-Darl+Di	S P, 150/150V, 15A, 175W, hFE>400	23a	TO-3	-	-	BDV 67D
MJ 11017	Mot	Si-N-Darl+Di	S P, 150/150V, 15A, 175W, hFE>400	23a	TO-3	-	-	BDV 66D
MJ 11018	Mot	Si-N-Darl+Di	S P, 150/150V, 15A, 175W, hFE>400	23a	TO-3	-	-	BDV 66D
MJ 11019	Mot	Si-P-Darl+Di	=MJ 11017: 200/200V	23a	TO-3	-	-	-
MJ 11020	Mot	Si-N-Darl+Di	=MJ 11018: 200/200V	23a	TO-3	-	-	-
MJ 11021	Mot	Si-P-Darl+Di	=MJ 11017: 250/250V	23a	TO-3	-	-	-
MJ 11022	Mot	Si-N-Darl+Di	=MJ 11018: 250/250V	23a	TO-3	-	-	-
MJ 11028	Mot	Si-N-Darl+Di	S P, 60V, 50A, 300W, hFE>1000	23a	TO-3	-	-	-
MJ 11029	Mot	Si-P-Darl+Di	S P, 60V, 50A, 300W, hFE>1000	23a	TO-3	-	-	-
MJ 11030	Mot	Si-N-Darl+Di	=MJ 11028: 90V	23a	TO-3	-	-	-
MJ 11031	Mot	Si-P-Darl+Di	=MJ 11029: 90V	23a	TO-3	-	-	-
MJ 11032	Mot	Si-N-Darl+Di	=MJ 11028: 120V	23a	TO-3	-	-	-
MJ 11033	Mot	Si-P-Darl+Di	=MJ 11029: 120V	23a	TO-3	-	-	-
MJ 12002	Mot	Si-N	TV-HA, 1500/750V, 2.6A, 75W	23a	TO-3	BU 208 A	23a	BU 205(A), BU 208(A), 2SD350(A), ++
MJ 12003	Mot	Si-N	TV-HA, 1500/750V, 4A, 100W	23a	TO-3	BU 508 A	18j	BU 500, BU 508(A), 2SC2928
MJ 12004	Mot	Si-N	TV-HA, 1500/750V, 5A, 100W	23a	TO-3	BU 508 A	18j	BU 500, BU 508(A), 2SC2928
MJ 12005	Mot	Si-N	TV-HA, 1500/750V, 8A, 100W	23a	TO-3	BU 508 A	18j	BU 508(A)
MJ 12010	Mot	Si-N	TV-HA, 950/400V, 10A, 100W	23a	TO-3	-	-	(BU 508(A), 2SD1279)7
MJ 12020	Mot	Si-N	HA, 850/450V, 5A, 125W, >15MHz	23a	TO-3	-	-	BUS 11(A), BUX 83, 2SD807, 2SD1103...04
MJ 12021	Mot	Si-N	HA, 850/450V, 8A, 150W, >15MHz	23a	TO-3	-	-	BUS 12(A), BUX 47(A), BUY 69A, BUY 70A
MJ 12022	Mot	Si-N	HA, 850/450V, 15A, 175W, >15MHz	23a	TO-3	-	-	BUS 13(A), BUX 48(A)
MJ 13010	Mot	Si-N	S P, -/400V, 30A, 175W, >6MHz	23a	TO-3	-	-	BUS 14(A), BUS 98(A), 2SC3058
MJ 13014	Mot	Si-N	S P, 550/350V, 10A, 150W	23a	TO-3	-	-	BUW 25...26, BUW 34...36, 2SC3046, ++
MJ 13015	Mot	Si-N	=MJ 13014: 600/400V	23a	TO-3	-	-	BUW 25...26, BUW 34...36, 2SC3046, ++
MJ 13070	Mot	Si-N	S P, 650/400V, 5A, 125W	23a	TO-3	BUW 11 A	18j	BUS 11(A), BUW 11(A), BUX 82...83, ++
MJ 13071	Mot	Si-N	=MJ 13070: 750/450V	23a	TO-3	BUW 11 A	18j	BUS 11(A), BUW 11(A), BUX 82...83, ++
MJ 13080	Mot	Si-N	S P, 650/400V, 8A, 150W	23a	TO-3	BUW 13 A	18j	BUS 12(A), BUW 12(A), BUW 35, BUW 132,++
MJ 13081	Mot	Si-N	=MJ 13080: 750/450V	23a	TO-3	BUW 13 A	18j	BUS 12(A), BUW 12(A), BUW 35, BUW 132,++
MJ 13090	Mot,Rca	Si-N	S P, 650/400V, 15A, 175W	23a	TO-3	BUW 13 A	18j	BUS 13(A), BUW 13(A), BUW 45...46, ++
MJ 13091	Mot,Rca	Si-N	=MJ 13090: 750/450V	23a	TO-3	BUW 13 A	18j	BUS 13(A), BUW 13(A), BUW 45...46, ++
MJ 13100	Mot	Si-N	S P, 650/400V, 20A, 175W	23a	TO-3	-	-	BUX 98AP, 2SC3094, 2SC3593, 2SC3988
MJ 13101	Mot	Si-N	=MJ 13100: 750/450V	23a	TO-3	-	-	BUX 98AP, 2SC3094, 2SC3593, 2SC3988
MJ 13330	Mot,Sgs	Si-N	S P, 400/200V, 20A, 175W	23a	TO-3	-	-	BUY 23...24, BUX 23...24, 2SC3085, ++
MJ 13331	Mot,Sgs	Si-N	=MJ 13330: 450/250V	23a	TO-3	-	-	BUY 23...24, BUX 23...24, 2SC3085, ++
MJ 13332	Mot,Sgs	Si-N	S P, 650/350V, 20A, 175W	23a	TO-3	-	-	2SC3085, 2SC3094, 2SC3216, 2SC3593
MJ 13333	Mot,Sgs	Si-N	=MJ 13332: 700/400V	23a	TO-3	-	-	2SC3094, 2SC3216, 2SC3593
MJ 13334	Mot,Sgs	Si-N	=MJ 13332: 750/450V	23a	TO-3	-	-	2SC3094, 2SC3216, 2SC3593
MJ 13335	Mot,Sgs	Si-N	=MJ 13332: 800/500V	23a	TO-3	-	-	2SC3094, 2SC3216, 2SC3593
MJ 14000	Mot	Si-N	LFS P, 60V, 60A, 300W	23a	TO-3	-	-	-
MJ 14001	Mot	Si-P	LFS P, 60V, 60A, 300W	23a	TO-3	-	-	-
MJ 14002	Mot	Si-N	=MJ 14000: 80V	23a	TO-3	-	-	-
MJ 14003	Mot	Si-P	=MJ 14001: 80V	23a	TO-3	-	-	-
MJ 15001	Mot,Rca	Si-N	LFS P, 140V, 15A, 200W, >2MHz	23a	TO-3	MJ 15015	23a	2N5631, 2SC2608, MJ 15015
MJ 15002	Mot,Rca	Si-P	LFS P, 140V, 15A, 200W, >2MHz	23a	TO-3	MJ 15016	23a	2N6031, 2SA1117, MJ 15016
MJ 15003	Mot,Rca	Si-N	LFS P, 140V, 20A, 250W, >2MHz	23a	TO-3	-	-	-
MJ 15004	Mot,Rca	Si-P	LFS P, 140V, 20A, 250W, >2MHz	23a	TO-3	-	-	-
MJ 15011	Mot	Si-N	S P, 250/250V, 10A, 200W	23a	TO-3	-	-	-
MJ 15012	Mot	Si-P	S P, 250/250V, 10A, 200W	23a	TO-3	-	-	-
MJ 15015	Mot	Si-N	LFS P, 200/120V, 15A, 180W, >0.8MHz	(MJ15016	23a	MJ 15015	23a	2SC2608
MJ 15016	Mot	Si-P	LFS P, 200/120V, 15A, 180W, >2MHz	(MJ15015	23a	MJ 15016	23a	2SA1117
MJ 15022	Mot,Rca	Si-N	LFS P, 350/200V, 16A, 250W, >4MHz	23a	TO-3	-	-	-
MJ 15023	Mot,Rca	Si-P	LFS P, 350/200V, 16A, 250W, >4MHz	23a	TO-3	-	-	-
MJ 15024	Mot,Rca	Si-N	=MJ 15022: 400/250V	23a	TO-3	-	-	-
MJ 15025	Mot,Rca	Si-P	=MJ 15023: 400/250V	23a	TO-3	-	-	-
MJ 15026	Mot	Si-N	LFS P, 200/200V, 16A, 250W, >15MHz	23a	TO-3	-	-	-
MJ 15027	Mot	Si-P	LFS P, 200/200V, 16A, 250W, >15MHz	23a	TO-3	-	-	-
MJ 16002	Mot	Si-N	S P, 850/450V, 5A, 125W, hFE>5	23a	TO-3	BUW 11 A	18j	BUS 11(A), BUW 11(A), BUX 83, 2SC3156,++