

2 SC 3316	Si-N	S-L, 500/400V, 2A, 40W, <500/1650ns	17j	BUX 84	17j
2 SC 3317	Si-N	S-L, 500/400V, 5A, 40W, <500/1650ns	17j	BUT 11 A	17j
2 SC 3318	Si-N	S-L, 500/400V, 10A, 80W, <500/1650ns	18j	BUW 13 A	18j
2 SC 3319	Si-N	S-L, 500/400V, 10A, 100W, <500/1650ns	23a	BUW 13 A	18j
2 SC 3320	Si-N	S-L, 500/400V, 15A, 80W, <500/1650ns	18j	BUW 13 A	18j
2 SC 3321	Si-N	S-L, 500/400V, 15A, 100W, <500/1650ns	23a	BUW 13 A	18j
2 SC 3322	Si-N	S-L, 900/800V, 5A, 80W, <1/4µs	18j	BUW 11 A	18j
2 SC 3323	Si-N	SMD, NF, ra, 60V, 0,15A, 150MHz	35a	BC 846	35a
2 SC 3325	Si-N	SMD, Uni, 50V, 0,5A, 300MHz	35a	BC 817	35a
2 SC 3327	Si-N	=2SC3326:	41c	-	-
2 SC 3328	Si-N	Uni, lo-sat, 80V, 2A, 0,9W, 100MHz	7c(9mm)	-	-
2 SC 3329	Si-N	NF, ra, 80V, 0,1A, 0,4W, 42MHz	7c	2SC2632	7c(9mm)
2 SC 3330	Si-N	Uni, 60V, 0,2A, 0,3W, 200MHz	40c	BC 546	7a
2 SC 3331	Si-N	=2SC3330: 0,5W	7c	BC 546	7a
2 SC 3332	Si-N	Uni, 180/160V, 0,7A, 0,7W, 120MHz	7c	-	-
2 SC 3333	Si-N	S, Vid, 250V, 0,05A, 0,6W, 100MHz	7c	2SC3468	7c(9mm)
2 SC 3334	Si-N	=2SC3333: 0,9W	7c(9mm)	2SC3468	7c(9mm)
2 SC 3335	Si-N	=2SC3333: 5W	14h	BF 471	14h
2 SC 3336	Si-N	S-L, 500/400V, 15A, 100W, <0,5/2µs	18j	BUW 13 A	18j
2 SC 3337	Si-N	VHF/UHF, 20V, 0,1A, 0,6W, 4,4GHz	7f	2SC2570 A	7f
2 SC 3339	Si-N	SMD, Uni, 60V, 0,15A, >80MHz	35d	-	-
2 SC 3341	Si-N	SMD, Uni, 35V, 0,5A, 300MHz	35d	-	-
2 SC 3342	Si-N	S-L, TV-HA, 1300/500V, 5A, 50W	23a	BU 208 A	23a
2 SC 3343	Si-N	S-L, TV-HA, 1200/500V, 5A, 50W	23a	BU 208 A	23a
2 SC 3344	Si-N	S-L, 500/400V, 8A, 60W, <3,5µs	≈15j	BUT 56 A	17j
2 SC 3345	Si-N	DC-DC Con., lo-sat, 60V, 12A, 40W, 90MHz	17j	2SC3346	17j
2 SC 3346	Si-N	=2SC3345: 80V, 80MHz	17j	2SC3346	17j
2 SC 3352	Si-N	S-L, 800/500V, 1,5A, 25W, <1/4µs	17c	2SC3752	17c
2 SC 3352 A	Si-N	=2SC3352: 900/500V, <1,2/7,2µs	17c	-	-
2 SC 3353	Si-N	S-L, 800/500V, 5A, 40W, <1/4µs	17c	BUT 11 AF	17c
2 SC 3353 A	Si-N	=2SC3353: 900/500V, <1,2/7,2µs	17c	BUT 11 AF	17c
2 SC 3354	Si-N	FM/VHF, 30V, 0,05A, 0,3W, 1200MHz	40c	2SC2570 A	7f
2 SC 3355	Si-N	UHF, 20V, 0,1A, 0,6W, 6,5GHz	7f	2SC3355	7f
2 SC 3356	Si-N	UHF, 20V, 0,1A, 0,2W, 7GHz	35a	2SC3356	35a
2 SC 3357	Si-N	SMD, UHF, 20V, 0,1A, 6,5GHz	39b	-	-
2 SC 3358	Si-N	UHF, 20V, 0,1A, 7GHz	25q	-	-
2 SC 3359(S)	Si-N	Uni, 80V, 0,3A, 0,4W, 150MHz	7c, 41c	BC 639	7a
2 SC 3361	Si-N	SMD, S, 60V, 0,15A, 120/390ns	35a	BC 846	35a
2 SC 3362	Si-N	S-L, 500/400V, 1,5A, 10W, <1/3µs	30j	(BUX 85)	17j
2 SC 3363	Si-N	S-L, 800/500V, 1A, 10W, <1/4µs	30j	(BUX 85)	17j
2 SC 3364	Si-N	NF/S-L, 160/160V, 1,5A, 20W, 200MHz	17j	2SC4159	17c
2 SC 3365	Si-N	S-L, 500/400V, 10A, 80W, <1/3,5µs	18j	-	-
2 SC 3366	Si-N	NF/S-L, 150/100V, 5A, 40W, <1/3,5µs	17j	2SC2334	17j
2 SC 3367	Si-N	NF/S-L, 120/80V, 5A, 40W, 300/900ns	17j	BD 243 C	17j
2 SC 3370	Si-N	NF/S-L, 200V, 15A, 150W, 30MHz	20j	2SC3264	20j
2 SC 3373	Si-N	UHF-0, 30V, 0,2A, 0,2W, 1500MHz	24b	2SC2570 A	7f
2 SC 3374	Si-N	SMD, VHF, TV-Tuner, 20V, 0,02A, 550MHz	35a	2SC3356	35a
2 SC 3375	Si-N	Uni, 30V, 0,8A, 0,6W, 120MHz	7c	BC 639	7c
2 SC 3376	Si-N	S-L, 900/800V, 3A, 60W, <5µs	18j	2SC3459	18j
2 SC 3377	Si-N	Uni, 40V, 1A, 0,5W, 150MHz	7c	BC 639	7c
2 SC 3378	Si-N	NF, ra, 120V, 0,1A, 0,2W, 100MHz	41c	2SC2632	7c(9mm)
2 SC 3381	Si-N	Dual, ra, 80V, 0,1A, 0,4W, 170MHz	7-SIP	-	-
2 SC 3382	Si-N	=2SC3383: ra	7c	2SC2632	7c(9mm)
2 SC 3383	Si-N	Uni, 60V, 0,2A, 0,5W, 250MHz	7c	BC 546	7a
2 SC 3384	Si-N	S-L, 500/400V, 15A, 120W, <2µs	23a	-	-
2 SC 3385	Si-N	S-L, 500/400V, 15A, 120W, <1,5µs	23a	-	-