

| Transistor Type No. | N P S | G S | Manufacturer | Lead Ident | Out- line | Maximum (V) | | | Maximum | | Max. T. ^o (C) | Frequency Resp.(MHz) | Leakage | | Gain | |
|---------------------|-------------|--------|--------------|---------------|--------------|-----------------|-------------------|-----------------|----------------|----------|-----------------------------|-------------------------|------------------------------------|-----------------|----------------------------------|--------|
| | | | | | | V _{CB} | V _{CE} ' | V _{EB} | I _C | Power | | | I _{CEO} @ V _{CB} | V _{CB} | h _{FE} @ I _C | |
| 25C99 | N | G | MAT | 211 | TO 18 | 20 | | 5.0 | .100A | .300W | 175J | 200.000G | 10UA | 20V | 80 | .010A |
| 25C101 | N | S | TOS | 605 | 605C | 60 | | 5.5 | 2.000A | 60.000W | 150J | 7.000G | 3MA | 20V | 74 | 1.000A |
| 25C102 | N | S | TOS | 405 | 405A | 50 | | 5.0 | 7.000A | 100.000W | 150J | 8.000G | 30MA | 50V | 30 | 5.000A |
| 25C103A | N | S | TOS | 210 | TO 18 | 30 | | 5.0 | .080A | .250W | 175J | 120.000G | 100NA | 15V | 80 | .010A |
| 25C104A | N | S | TOS | 210 | TO 18 | 30 | | 5.0 | .080A | .250W | 175J | 100.000G | 100NA | 15V | 80 | .010A |
| 25C105 | N | S | TOS | 210 | TO 18 | 30 | | 5.0 | .080A | .250W | 175J | 120.000G | 5NA | 15V | 80 | .001A |
| 25C106 | N | S | TOS | 170 | TO 8 | 60 | | 5.0 | 2.000A | 15.000W | 150J | 30.000G | 3MA | 30V | 20 | .500A |
| 25C107 | N | S | TOS | 170 | TO 8 | 60 | | 5.0 | 1.500A | 15.000W | 150J | 30.000G | 3MA | 30V | 20 | .500A |
| 25C108 | N | S | TOS | 210 | TO 5 | 90 | | 5.0 | .600A | .600W | 150J | 100.000G | 1UA | 30V | 40 | .150A |
| 25C109 | N | S | TOS | 210 | TO 5 | 50 | | 5.0 | .600A | .600W | 150J | 70.000G | 1UA | 30V | 40 | .150A |
| 25C112 | -N | S | HIT | 211 | TO 5 | 40 | 20 | 5.0 | .200A | .750W | 175J | 180.000B | 1UA | 20V | 80 | |
| 25C113 | -N | S | HIT | 211 | TO 5 | 50 | 25 | 5.0 | .200A | .750W | 175J | 180.000B | 1UA | 20V | 80 | |
| 25C115-1 | -N | S | SON | 211 | 211C | 30 | 25R | 5.0 | .050A | .750W | 175J | 100.000G | 3UA | 30V | 140 | |
| 25C115-2 | -N | S | SON | 211 | 211C | 45 | 45R | 5.0 | .050A | .750W | 175J | 100.000G | 3UA | 30V | 140 | |
| 25C115-3 | -N | S | SON | 211 | 211C | 70 | 70R | 5.0 | .050A | .750W | 175J | 100.000G | 3UA | 30V | 140 | |
| 25C116 | N | S | HIT | 211 | TO 5 | 50 | 25 | 5.0 | .200A | .750W | 175J | 70.000G | 1UA | 20V | 52 | .200A |
| 25C117 | N | S | HIT | 171 | TO 8 | 75 | 50 | 5.0 | .600A | 2.000W | 175J | 60.000G | 5UA | 40V | 10 | |
| 25C118 | -N | S | HIT | 171 | TO 8 | 80 | | 5.0 | .600A | 2.000W | 175J | 70.000G | 5UA | 40V | 10 | |
| 25C119 | -N | S | HIT | 171 | TO 8 | 75 | | 5.0 | .600A | 2.000W | 175J | 70.000G | 5UA | 40V | 10 | |
| 25C125 | -N | S | SON | 211 | 211C | 100 | 100R | 5.0 | .050A | .750W | 175J | 100.000G | 3UA | 30V | 80 | |
| 25C126 | -N | S | SON | 211 | 211C | 140 | 140R | 5.0 | .050A | .750W | 175J | 100.000G | 3UA | 30V | 80 | |
| 25C128 | N | G | MAT | 212 | TO 5 | 30 | | 20.0 | .100A | .125W | 75J | 4.000G | 3UA | 5V | 30 | .200A |
| 25C129 | N | G | MAT | 212 | TO 5 | 25 | | 20.0 | .100A | .125W | 75J | 6.000G | 3UA | 5V | 40 | .200A |
| 25C141 | N | S | OKI | 211 | TO 18 | 20 | 12 | 4.0 | .200A | .360W | 175J | 150.000G | 200NA | 15V | 40 | |
| 25C142 | N | S | OKI | 211 | TO 18 | 30 | 14 | 5.0 | .200A | .360W | 175J | 200.000G | 100NA | 15V | 40 | |
| 25C143 | N | S | OKI | 211 | TO 18 | 40 | 18 | 5.0 | .200A | .360W | 175J | 260.000G | 100NA | 15V | 60 | |
| 25C144 | N | S | OKI | 211 | TO 18 | 50 | 25 | 5.0 | .200A | .360W | 175J | 260.000G | 100NA | 15V | 60 | |
| 25C144A | N | S | OKI | 211 | TO 18 | 60 | 30 | 5.0 | .200A | .360W | 175J | 260.000G | 100NA | 15V | 60 | |
| 25C147A | -N | S | SON | 211 | 211C | 30 | 25R | 5.0 | 1.000A | .750W | 175J | 100.000G | 5UA | 30V | 70 | |
| 25C147B | -N | S | SON | 211 | 211C | 60 | 40R | 5.0 | 1.000A | .750W | 175J | 100.000G | 5UA | 30V | 70 | |
| 25C150 | N | S | HIT | 211 | TO 5 | 20 | | 5.0 | .100A | .750W | 175J | 100.000B | 1UA | 20V | 50 | |
| 25C151 | N | S | HIT | 211 | TO 5 | 40 | | 5.0 | .100A | .750W | 175J | 130.000B | 1UA | 20V | 50 | |
| 25C152 | N | S | HIT | 211 | TO 5 | 60 | | 5.0 | .100A | .750W | 175J | 160.000B | 1UA | 20V | 50 | |
| 25C153 | -N | S | HIT | 211 | TO 5 | 120 | | 40.0 | .100A | .750W | 175J | 350.000B | 1UA | 120V | 40 | |
| 25C154 | N | S | HIT | 211 | TO 5 | 120 | 70 | 5.0 | .100A | .750W | 175J | 200.000G | | | 50 | .010A |
| 25C154A | N | S | HIT | 211 | TO 5 | 150 | | 5.0 | .100A | .750W | 175J | 220.000G | | | 50 | .010A |
| 25C154B | N | S | HIT | 211 | TO 5 | 180 | | 5.0 | .100A | .750W | 175J | 220.000G | | | 50 | .010A |
| 25C154C | N | S | HIT | 211 | TO 5 | 200 | | 6.0 | .100A | .750W | 175J | 120.000G | 100NA | 100V | 90 | .025A |
| 25C161 | N | S | TOS | 605 | TO 3 | 60 | | 5.5 | 4.000A | 50.000W | 150J | 10.000G | 2MA | 30V | 40 | 3.000A |
| 25C162 | N | S | OKI | 211 | TO 5 | 30 | 14 | 5.0 | .250A | .600W | 175J | 130.000G | 100NA | 15V | 60 | |
| 25C163 | N | S | OKI | 211 | TO 5 | 50 | 25 | 5.0 | .250A | .600W | 175J | 260.000G | 100NA | 15V | 70 | |
| 25C164 | N | S | OKI | 211 | TO 5 | 60 | 30 | 5.0 | .250A | .600W | 175J | 260.000G | 100NA | 15V | 70 | |
| 25C165 | N | S | OKI | 211 | TO 5 | 60 | 30 | 5.0 | .300A | .900W | 175J | 260.000G | 100NA | 15V | 70 | |