

2 SC 3576	Say	Si-N	30/25V, hi-Ueb=15V, 0,3/0,5A, 0,5W, 250MHz hi-hFE=800...3200, lo-sat<0,5V(0,2A)	41c					2SC3068, 2SC3836
2 SC 3577	Mat	Si-N	S P, 850/650V, 5/10A, 80W, 6MHz, <1/3µs	16c	(TOP-3F)	(BUW 11 A) ³	18j		BUW 11F, 2SC4300, 2SC4457
2 SC 3578	Hit	Si-N	SMD, S, 40/15V, 0,1A, <40/70ns	35a	SOT-23				-
2 SC 3579	Shi	Si-N	S P, 800/800V, 6/12A, 50W, 8MHz, <0,5/3,7µs	17j	TO-220	BUT 11 A	17j		BUT 11A, BUW 46A, 2SC3050, 2SC3047++
2 SC 3580	Mit	Si-N	LF Drv,Out, 25/20V, 0,7/1A, 0,9W, 180MHz	{2SA1398	7c(9mm)	TO-92L	BC 337	7a	BC 337...338, 2SC2236, 2SD863, 2SD1331,++
2 SC 3581	Mit	Si-N	LF Drv,Out, 55/50V, 0,4/0,6A, 0,9W, 150MHz	{2SA1399	7c(9mm)	TO-92L	BC 639	7c	BC 637, 2SC3939, 2SD863, 2SD1937, ++
2 SC 3582	Nec	Si-N	UHF, 20/10V, 65mA, 0,6W, 8GHz, F=1,2dB(1GHz)	7f	TO-92				-
2 SC 3583	Nec	Si-N	SMD, UHF, 20/10V, 65mA, 9GHz, F=1,2dB(1GHz)	35a	SOT-23				-
2 SC 3584	Nec	Si-N	UHF, 20/10V, 65mA, 0,2W, 9GHz, F=1,2dB(1GHz)	25q	≈SOT-103				-
2 SC 3585	Nec	Si-N	SMD, UHF, 20/10V, 35mA, 10GHz, F=1,8dB(2GHz)	35a	SOT-23				-
2 SC 3586	Nec	Si-N	UHF, 20/10V, 35mA, 0,25W, 10GHz, F=1,8dB(900MHz)	25q	≈SOT-103				-
2 SC 3587	Nec	Si-N	UHF, 20/10V, 35mA, 0,58W, 10GHz, F=1,7dB(2GHz)	51s	SOT-173				-
2 SC 3588	Nec	Si-N	S P, 500/400V, 0,5/1A, 10W, <1/3,5µs	{2SA1400	30j	TO-251	(BUX 85) ⁶	17j	2SC3075, 2SC3129, 2SC4499, (BUX 84...85) ⁶
						Z: TO-252			
2 SC 3589	Say	Si-N	HA, hi-def, 250/100V, 7/15A, 40W, 10MHz lo-sat<0,8V(5A)	17j	TO-220	(BU 406)	17j		(BU 406...408, 2SC3173, 2SC3175)
2 SC 3590	Say	Si-N	HA, hi-def, 330/150V, 7/12A, 50W, 40MHz lo-sat<0,8V(5A)	17j	TO-220	(BU 406)	17j		(BU 406...408, 2SC3173, 2SC3175)
2 SC 3591	Say	Si-N	=2SC3590: 400/200V	17j	TO-220	(BU 406)	17j		(BU 406, BU 408, 2SC3175)
2 SC 3592	Nec	Si-N	LF S P, 60/60V, 5A, 10W, <1/3,5µs	30j	TO-251/252	(BD 243 C) ⁴	17j		2SC3074, 2SC3518, 2SD1803, (BDV 10...12++) ⁴
2 SC 3593	Mat	Si-N	S P, 850V, 25A, 150W, <3/2,5µs	23a	TO-3				BUS 14(A), BUS 98(A)
2 SC 3594	Hit	Si-N	S P, 1400/650V, 8A, 50W, <500/5,5µs	23a	TO-3	BU 508 A	18j		BU 508(A), BU 908, MJ 8505, 2SC4284...85
2 SC 3595	Say	Si-N	Vid Out, hi-def, 30/20V, 0,5/1A, 5W, 2GHz	14h	TO-126				-
2 SC 3596	Say	Si-N	Vid, hi-def, 80/60V, 0,3/0,6A, 8W, 700MHz	{2SA1402	14h	TO-126	2SC3599	14h	2SC3599, 2SC3951
2 SC 3597	Say	Si-N	Vid, hi-def, 80/60V, 0,5/1A, 10W, 800MHz	{2SA1403	14h	TO-126	2SC3597	14h	2SC3952
2 SC 3598	Say	Si-N	Vid, hi-def, 120/120V, 0,2/0,4A, 8W, 500MHz	{2SA1404	14h	TO-126	2SC3599	14h	2SC3599, 2SC3953
2 SC 3599	Say	Si-N	Vid, hi-def, 120/120V, 0,3/0,6A, 8W, 500MHz	{2SA1405	14h	TO-126	2SC3599	14h	2SC3954
2 SC 3600	Say	Si-N	Vid, hi-def, 200/200V, 0,1/0,2A, 7W, 400MHz	{2SA1406	14h	TO-126	2SC3601	14h	2SC3601, 2SC3955
2 SC 3601	Say	Si-N	Vid, hi-def, 200/200V, 0,15/0,3A, 7W, 400MHz	{2SA1407	14h	TO-126	2SC3601	14h	2SC3956
2 SC 3602	Tos	Si-N	UHF 25/20V, 0,02A, 0,2W, 1100MHz, Gp=18dB(800MHz)	25p	SOT-103		2SC2466	25p	2SC2464, 2SC2466, 2SC2144, 2SC2360, ++
2 SC 3603	Nec	Si-N	UHF, 20/12V, 0,1A, 0,58W, 7GHz, F<3,4dB(2GHz)	51s	SOT-173				2SC3358
2 SC 3604	Nec	Si-N	UHF, 20/16V, 0,065A, 0,58W, 8GHz, F<2,3dB(2GHz)	51s	SOT-173				2SC3358
2 SC 3605	Tos	Si-N	UHF, 20/12V, 0,08A, 0,6W, 6,5GHz, F<3dB(1GHz)	7f	≈TO-92	2SC3355	7f		2SC2570(A), 2SC3037, 2SC3512, 2SC3355
2 SC 3606	Tos	Si-N	=2SC3605: SMD, 7GHz, F<2dB(1GHz)	35a	SOT-23	2SC3356	35a		BFR 193, 2SC3356, 2SC3445, 2SC5084
2 SC 3607	Tos	Si-N	=2SC3605: SMD	39b	SOT-89				BFQ 193, 2SC3301, 2SC3357...58, 2SC4988
2 SC 3608	Tos	Si-N	=2SC3605: 7GHz, F<2dB(1GHz)	25q	SOT-103				BFQ 82, 2SC2876, 2SC3358
2 SC 3609	Tos	Si-N	=2SC3605: SMD, 7GHz, F<2dB(1GHz)	44u	SOT-143				-
2 SC 3610	Mat	Si-N	Vid P, hi-res, 110/50V, 0,15/0,3A, 10W, 300MHz	17j	TO-220	2SC3782	17j		2SC3781
2 SC 3611	Mat	Si-N	=2SC3610: 4W	14h	TO-126				2SC3598...99
2 SC 3612	Tos	Si-N	Vid, hi-res, 180/150V, 0,3/0,5A, 20W, 400MHz	{S3746	17j	TO-220			-
2 SC 3613	Tos	Si-N	Vid Drv, hi-res, 20/18V, 0,5/0,8A, 5W, 3500MHz	14b	TO-126 Iso				-
2 SC 3614	Hit	Si-N	SMD, VHF/UHF, 20/15V, 0,1A, Gp>6dB(900MHz)	39b	SOT-89				-
2 SC 3615	Nec	Si-N	50/50V, hi-Ueb=15V, 0,3/0,5A, 220MHz hi-hFE=800...3200, 150/1100ns	7c	TO-92				2SC3836, 2SD1915
2 SC 3616	Nec	Si-N	25/25V, hi-Ueb=15V, 0,7/1A, 250MHz hi-hFE=800...3200, 130/1100ns	7c	TO-92				2SC3070, 2SC4204, 2SD1582
2 SC 3617	Nec	Si-N	=2SC3615: SMD	39b	SOT-89				-
2 SC 3618	Tos	Si-N	=2SC3616: SMD	39b	SOT-89				2SC3650
2 SC 3619	Tos	Si-N	Vid P, CTV-HA Drv, 300/300V, 0,1A, >50MHz	14b	TO-126 Iso	(BF 471) ³	14h		2SC3789...90, (BF 758...759, MPS-U10,++) ⁴
2 SC 3620	Tos	Si-N	Vid P, CTV-HA Drv, 300/300V, 0,1A, >50MHz	14b	TO-126 Iso	(BF 471) ³	14h		2SC3789...90, (BF 758...759, MPS-U10,++) ⁴
2 SC 3621	Tos	Si-N	CTV-HA, LF P, 150/150V, 1,5A, 10W, 100MHz	{2SA1408	14b	TO-126 Iso	(2SC3117) ³	14h	2SC3902, (2SC3117, 2SD669, 2SD781) ³
2 SC 3622(A)	Nec	Si-N	60/50V, hi-Ueb=12V, 0,15A, 0,25W, 250MHz hi-hFE=1000...3200, 130...1220ns	7c	TO-92	2SC3071	7c(9mm)		2SC3069, 2SC3836
2 SC 3623(A)	Nec	Si-N	=2SC3622:	40c	(SST)	2SC3071	7c(9mm)		2SC3069, 2SC3836
2 SC 3624(A)	Nec	Si-N	=2SC3622: SMD	35a	SOT-23				2SC3689
2 SC 3625	Tos	Si-N	S P, DC-DC Conv., 500/400V, 8/10A, 60W, <1/3,5µs	17j	TO-220	BUT 56 A	17j		BUT 54, BUT 56(A), 2SC3562, 2SC4107, ++
2 SC 3626	Tos	Si-N	=2SC3625: 40W	17c	SOT-186	BUT 12 AF	17c		2SC3574...75, 2SC3890, 2SC4130, 2SC4161++
2 SC 3627	Tos	Si-N	S-Reg, 250/200V, 10/15A, 40W, <1/3,5µs	17c	SOT-186				2SC3572, 2SC3575, 2SC4162, 2SD1795, ++
2 SC 3628	Mit	Si-N	VHF P, 35/17V, 2A, PQ=6,5W(175MHz/13,5V)	58s					-
2 SC 3629	Mit	Si-N	UHF P, 20/9V, 1A, PQ=1,5W(520MHz/7,2V)	58s					-
2 SC 3630		Si-N	UHF P, 35/17V, 1A, PQ=3,3W(520MHz/7,2V)	58s					-
2 SC 3631(Z)	Nec	Si-N	S P, 500/400V, 2/4A, 10W, 50MHz, <0,5/2,7µs	{2SA1412	30j	TO-251			2SC3233, (BUV 93...94) ⁶
						Z: TO-252			
2 SC 3632(Z)	Nec	Si-N	S P, 600/600V, 1/2A, 10W, 30MHz <0,5/5,5µs	{2SA1413	30j	TO-251/252			2SC3363
						Z: TO-252			
2 SC 3633	Say	Si-N+Di	=2SC3636: integr. Damper-Diode	18j	TO-3P				2SC3639
2 SC 3634	Say	Si-N+Di	=2SC3637: integr. Damper-Diode	18j	TO-3P				2SC3640
2 SC 3635	Say	Si-N+Di	=2SC3638: integr. Damper-Diode	18j	TO-3P				2SC3641
2 SC 3636	Say	Si-N	HA, hi-def, 900/500V, 7/14A, 80W, sat<2V(4A)	18j	TO-3P	2SC3688	18j		2SC3643
2 SC 3637	Say	Si-N	HA, hi-def, 900/500V, 10/20A, 90W, sat<2V(5A)	18j	TO-3P	2SC3688	18j		2SC3644
2 SC 3638	Say	Si-N	HA, hi-def, 900/500V, 15/25A, 100W, sat<2V(7A)	18j	TO-3P				-
2 SC 3639	Say	Si-N+Di	=2SC3642: integr. Damper-Diode	18j	TO-3P				-
2 SC 3640	Say	Si-N+Di	=2SC3643: integr. Damper-Diode	18j	TO-3P				-
2 SC 3641	Say	Si-N+Di	=2SC3644: integr. Damper-Diode	18j	TO-3P				-
2 SC 3642	Say	Si-N	HA, hi-def, 1200/800V, 6/12A, 100W, sat<5V(4A)	18j	TO-3P				2SC3686...87
2 SC 3643	Say	Si-N	HA, hi-def, 1200/800V, 8/16A, 140W, sat<5V(6A)	18j	TO-3P	2SC3466	18j		2SC3466
2 SC 3644	Say	Si-N	HA, hi-def, 1200/800V, 12/25A, 150W, sat<5V(8A)	18j	TO-3P				-
2 SC 3645	Say	Si-N	SMD, 180/160V, 0,14/0,2A, 150MHz	{2SA1415	39b	SOT-89			BFN 16, BFN 18
2 SC 3646	Say	Si-N	SMD, 120/100V, 1/2A, 120MHz, 80/900ns	{2SA1416	39b	SOT-89			2SC3647, 2SC4132, 2SC4373, 2SD1418...19
2 SC 3647	Say	Si-N	SMD, 120/100V, 2/3A, 120MHz, 80/1050ns	{2SA1417	39b	SOT-89			2SC4132
2 SC 3648	Say	Si-N	SMD, 180/160V, 0,7/1,5A, 120MHz, 50/1060ns	{2SA1418	39b	SOT-89			2SC3649, 2SD1420...1421
2 SC 3649	Say	Si-N	SMD, 180/160V, 1,5/2,5A, 120MHz, 40/1280ns	{2SA1419	39b	SOT-89			2SD1420...1421
2 SC 3650	Say	Si-N	SMD, 30/25V, hi-Ueb=15V, 1,2/2A, 220MHz hi-hFE=800...3200	39b	SOT-89				(2SD1950)
2 SC 3651	Say	Si-N	SMD, 120/100V, hi-Ueb=15V, 0,2/0,3A, 150MHz hi-hFE=500...3200	39b	SOT-89				-
2 SC 3652	Hit	Si-N	HF P, 30/20V, 0,3/0,5A, 5W, 1200MHz	14h	TO-126				-
2 SC 3653	Say	Si-N+R	=2SC3399: 0,4W	{2SA1420	7c	TO-92	→2SC3399		→2SC3399
2 SC 3654	Say	Si-N+R	=2SC3400: 0,4W	{2SA1421	7c	TO-92	→2SC3400		→2SC3400
2 SC 3655	Say	Si-N+R	=2SC3401: 0,4W	{2SA1422	7c	TO-92	→2SC3401		→2SC3401
2 SC 3656	Say	Si-N+R	=2SC3402: 0,4W	{2SA1423	7c	TO-92	→2SC3402		→2SC3402
2 SC 3657	Tos	Si-N	S P, 900/800V, 4/8A, 80W, <1/3,5µs	18j	TO-3P	BUW 11A	18j		BUW 11A, 2SC3153, 2SC3232, 2SC3535, ++