

TRANSISTOR NUMBER	PM OA LT	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE	MFR	EUR EQUIV	USA EQUIV	ISS
25C733	NS	T098	L21	35V	30V	5V	100MA	125C	300MWF	80M	14P	70MN	2MA	ALG	TOS	BC182L	2N3710	0
25C733/B	NS	T098	L21	35V	30V	5V	100MA	125C	300MWF	80M	14P	350MN	2MA	ALG	TOS	BC182L	2N3710	0
25C733/G	NS	T098	L21	35V	30V	5V	100MA	125C	300MWF	80M	14P	200MN	2MA	ALG	TOS	BC182L	2N3710	0
25C733/Y	NS	T098	L21	35V	30V	5V	100MA	125C	300MWF	80M	14P	120MN	2MA	ALG	TOS	BC182L	2N3710	0
25C733/0	NS	T098	L21	35V	30V	5V	100MA	125C	300MWF	80M	14P	70/140	2MA	ALG	TOS	BC182L	2N3710	0
25C734	NS	T098	L21	70V	50V	5V	150MA	125C	300MWF	75M	10P	40MN	20MA	ALH	TOS	BC182L	2N3710	0
25C734/G	NS	T098	L21	70V	50V	5V	150MA	125C	300MWF	75M	10P	200MN	20MA	ALH	TOS	BC182L	2N3710	0
25C734/R	NS	T098	L21	70V	50V	5V	150MA	125C	300MWF	75M	10P	40/80	20MA	ALH	TOS	BC182L	2N3710	0
25C734/Y	NS	T098	L21	70V	50V	5V	150MA	125C	300MWF	75M	10P	120MN	20MA	ALH	TOS	BC182L	2N3710	0
25C734/0	NS	T098	L21	70V	50V	5V	150MA	125C	300MWF	75M	10P	70/140	20MA	ALH	TOS	BC182L	2N3710	0
25C735	NS	T098	L21	35V	30V	5V	400MA	125C	300MWF	150M	14P	40/400	100MA	AMG	TOS	BCW36	2N3704	0
25C735/G	NS	T098	L21	35V	30V	5V	400MA	125C	300MWF	150M	14P	200MN	100MA	AMG	TOS	BCW36	2N3704	0
25C735/R	NS	T098	L21	35V	30V	5V	400MA	125C	300MWF	150M	14P	40/90	100MA	AMG	TOS	BCW36	2N3704	0
25C735/Y	NS	T098	L21	35V	30V	5V	400MA	125C	300MWF	150M	14P	120MN	100MA	AMG	TOS	BCW36	2N3704	0
25C735/0	NS	T098	L21	35V	30V	5V	400MA	125C	300MWF	150M	14P	70/140	100MA	AMG	TOS	BCW36	2N3704	0
25C736	NS	T03	L05	135V	60V	5V	5A	175C	50WC			25/70	1A	RHG	OBS	BDY23	2N3445	0
25C737	NS	X28	L65	60V	40V	4V	1A5	125C	25WC	150M		20MN	100MA	VHP				1
25C738	NS	T092	L21	25V	12V	4V	20MA	125C	150MWF	200M	3P	60TP	1MA	VLA	MIT	BFX73	2N918	0
25C739	NS	T092	L21	25V	12V	4V	20MA	125C	150MWF	175M	3P	60TP	1MA	VLA	MIT	BFX73	2N918	0
25C740	NS	T01	L02	25V	12V	2V	20MA	175C	150MWF	450M	3P	40TP	10MA	VLA	MIT	BFX73	2N918	0
25C741	NS	T039	L04	40V	24V	3V	300MA	175C	800MWF	250M	6P	30TP	100MA	VMA	MIT	BSW54	2N2219A	0
25C742	NS	T060	L61	65V	40V	4V	1A5	175C	12 5WC	200M		15MN	150MA	VHP				1
25C743	NS	T060	L61	65V	40V	4V	3A	175C	25WC	175M		15MN	300MA	VHP				1
25C745	NS	T060	L61	50V	30V		1A5	175C	12 5WC	225M		20MN	150MA	VHP				1
25C746	NS	T060	L61	45V	30V	4V	3A	175C	25WC	200M		15MN	300MA	VHP				1
25C748	NS	T060	L61	36V	24V		1A5	175C	12 5WC	200M		10MN	150MA	VHP				1
25C749	NS	T060	L61	36V	24V	4V	3A	175C	25WC	175M		10MN	300MA	VHP				1
25C751	NS	T018	L01	20V		2V	20MA	150C	100MWF	325M		20MN	8MA	VLA		BFX73	2N918	1
25C752	NS	T098	L21	30V	12V	4V	100MA	125C	100MWF	150M	8P	80TP	10MA	VLS	TOS	BSX20	2N2369	0
25C752G	NS	T098	L21	40V	15V	5V	200MA	125C	200MWF	200M	6P	40/240	10MA	VLS	TOS	BSX20	2N2369	0
25C752G/R	NS	T098	L21	40V	15V	5V	200MA	125C	200MWF	200M	6P	40/80	10MA	VLS	TOS	BSX20	2N2369	0
25C752G/Y	NS	T098	L21	40V	15V	5V	200MA	125C	200MWF	200M	6P	120MN	10MA	VLS	TOS	BSX20	2N2369	0
25C752G/0	NS	T098	L21	40V	15V	5V	200MA	125C	200MWF	200M	6P	70/140	10MA	VLS	TOS	BSX20	2N2369	0
25C753	NS	X37		25V		3V	20MA	150C	100MWF	550M		30MN	2MA	TUG		BF180		1
25C754	NS	X37		20V		5V	150MA	150C	150MWF	45M		40MN	20MA	ALN		BC184L	2N3707	1
25C755	NS	X37		15V		5V	100MA	150C	150MWF	50M		100MN	300MA	ALN		BC109C	2N930	1
25C756	NS	T05	L04	130V	40V	6V	4A	150C	10WC	30M		80MN	100MA	AMH	SOY	BSW66	2N1893	0
25C756A	NS	T05	L04	100V	60V	6V	4A	175C	10WC	70M	90P	27/264	100MA	RHH	SOY	BSV64	2N5152	2
25C756-2	NS	T05	L04	100V	60V	6V	4A	175C	10WC	32M	70P	30/173	100MA	AHH	SOY	BSS45	2N5152	2
25C756-3	NS	T05	L04	130V	80V	6V	4A	175C	10WC	32M	70P	30/173	100MA	AHH	SOY	BSS45	2N5152	2
25C756-4	NS	T05	L04	150V	100V	6V	4A	175C	10WC	32M	70P	30/173	100MA	AHH	SOY	BUY48	2N5238	2
25C757	NS	X37		30V		3V	20MA	150C	100MWF	550M		30MN	2MA	TUG		BF180		1
25C758	NS	T03	L05	280V		5V	8A	150C	60WC	10M		15MN	500MA	RHE		BUX16C	2N5157	1
25C759	NS	T03	L05	180V		5V	8A	150C	60WC	10M		15MN	500MA	RHE		BDY25		1
25C760	NS	T03	L05	100V		5V	8A	150C	60WC	10M		15MN	500MA	RHE		BUX16		1
25C761	NS	T072	L06	30V	20V	2V	20MA	175C	150MWF	330M	OR56	13MN	2MA	TUG	MAT	BF180		0
25C762	NS	T072	L06	30V	20V	3V	20MA	175C	150MWF	300M	OR56	13MN	2MA	TUG	MAT	BF181		0
25C763	NS	T092	L21	25V	12V	3V	20MA	125C	100MWF	235M	3P	70TP	1MA	VLA	MIT	BFX73	2N918	0
25C764	NS	T018	L01	40V	15V	4V	500MA	175C	350MWF	500M	4P	40MN	10MA	VLS	NIP	BSX20	2N2369A	0
25C765	NS	T03	L05	60V	40V	6V	2A	150C	30WC			30MN	1A	RHP		BDY24	2N3448	1
25C766	NS	T03	L05	120V	80V	5V	2A	150C	30WC			20/180	1A	RHH	OBS	BU123		0
25C767	NS	T03	L05	180V	120V	5V	2A	150C	30WC			20/180	1A	RHH	OBS	BU123		0
25C768	NS	T03	L05	60V	40V	5V	10A	150C	50WC			10MN	2A	RHS		BDY23	2N3448	1
25C769	NS	T03	L05	120V	80V	5V	10A	150C	50WC			10/110	2A	RHH	OBS	BU123		0
25C770	NS	T03	L05	200V	100V		10A	150C	50WC			10/110	2A	RHH	OBS	BU123		0
25C772	NS	T092	L21	15V		3V	30MA	125C	120MWF	150M		30MN	1MA	VLA		BFX73	2N918	1
25C773	NS	T092	L21	50V	30V	5V	200MA	125C	250MWF	125M	14P	35MN	10MA	AMG	MIT	BCW36	2N3704	0
25C774	NS	T039	L04	50V	30V	4V	500MA	200C	800MWF	100M	20P	20MN	100MA	RMG	MIT	BSW54	2N2219A	0
25C775	NS	T039	L04	75V	50V	4V	1A	200C	800MWF	100M	20P	5MN	500MA	RMG	MIT	BSW54	2N2219A	0
25C775A	PS	TOP66	L32	120V	120V	4V	700MA	150C	10WC	20M		35/200	50MA	AME	HIJ			2
25C776	NS	T039	L04	75V	50V	4V	1A	200C	1WF	100M	20P	5MN	500MA	RMG	MIT	BSW54	2N2219A	0
25C777	NS	T037	L47	75V	50V	4V	1A	200C	2WF	75M	20P	5MN	500MA	RMG	MIT	BDY78		0
25C778	NS	T066	L43	80V	50V	4V	2A	200C	2500MWF	75M	20P	5MN	500MA	RHG	MIT	BDY78		0
25C779	NS	T066	L43	300V		6V	2A	150C	20WC	5M		40MN	100MA	RHE	TOS	BUX67C	2N3585	1
25C780	NS	T098	L21	70V	70V	2V	20MA	125C	200MWF	50M	5P	60TP	2MA	ALH	TOS	BC394		0
25C780G	NS	T098	L21	80V	80V	5V	20MA	125C	100MWF	50M	7P	40MN	2MA	ALH	TOS	BC394		0
25C780AG	NS	T098	L21	150V	150V	5V	30MA	125C	150MWF	50M	7P	40/240	2MA	ALH	TOS	BC394		0
25C781	NS	T05	L04	75V	40V	5V	1A	175C	800MWF	175M	20P	80TP	150MA	RMG	NIP	BSW54	2N2219A	0
25C782	NS	T066	L43	300V	300V	5V	1500MA	150C	20WC	5M	100P	30/250	100MA	RHE	TOS		2N3739	0
25C782A	NS	T066	L43	300V	300V	5V	1500MA	150C	25WC	5M	100P	40/350	100MA	RHE	TOS		2N3739	0
25C783	NS	T066	L43	200V	200V	5V	1500MA	150C	25WC	5M	100P	30/250	100MA	RHE	TOS		2N3739	0
25C784	NS	T098	L21	40V	30V	4V	20MA	125C	100MWF	250M	OR9	25/140	1MA	FGV	TOS	BF200		0
25C784/B	NS	T098	L21	40V	30V	4V	20MA	125C	100MWF	250M	OR9	25/50	1MA	FGV	TOS	BF200		0
25C784/R	NS	T098	L21	40V	30V	4V	20MA	125C	100MWF	250M	OR9	40/80	1MA	FGV	TOS	BF200		0
25C784/0	NS	T098	L21	40V	30V	4V	20MA	125C	100MWF	250M	OR9	70/140	1MA	FGV	TOS	BF200		0