

TRANSISTOR NUMBER	PM OA LT	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE	MFR	EUR EQUIV	USA EQUIV	ISS
25C857H	NS	T01	L02	150V	150V	5V	200MA	175C	200MWF	25M	20P	30MN	10MA	ALH	HIJ	BSX21	2N1990R	0
25C858	NS	T092	L21	20V	12V	5V	50MA	125C	100MWF	90M	6P	240TP	1MA	ALN	SAN	BC184L	2N3707	0
25C859	NS	T092	L21	20V	12V	5V	50MA	125C	100MWF	90M	6P	240TP	1MA	ALN	SAN	BC184L	2N3707	0
25C860	NS	T072	L06	15V	12V	3V	30MA	125C	200MWF	400M	2P2	80TP	1MA	VLA	SAN	BFX73	2N918	0
25C861	NS	T03	L05	450V		6V	1A	150C	50WC	3M		20MN	200MA	RHE		BU109	2N6251	1
25C862	NS	T03	L05	650V		6V	5A	150C	50WC	3M		5MN	3A5	RHE		BDY96		1
25C863	NS	T072	L06	60V	40V	4V	25MA	150C	200MWF	300M		40MN	7MA	TIA	TOS	BF173		1
25C864	NS	T072	L06	40V	30V	4V	25MA	150C	200MWF	360M	OR5	39MN	7MA	TIA	TOS	BF173		0
25C865	NS	T08	L12	60V		6V	2A	175C	20WC			30MN	1A	RHP			2N2782	1
25C866	NS	T037	L47	60V		6V	1A5	175C	5WC			30MN	400MA	RMP			2N2197	1
25C867	NS	T066	L43	520V		10V	1A	175C	18WC	4M		40MN	100MA	RME	SOY		2N4240	1
25C868	NS	T092	L40	130V	40V	5V	30MA	125C	200MWF	75M		35MN	1MA	RLH	MIT	BSX21	2N1990R	0
25C869	NS	T092	L40	160V	40V	5V	30MA	125C	200MWF	75M		35MN	1MA	RLH	MIT	BSX21	2N1990R	0
25C870	NS	T092	L40	30V	25V	4V	30MA	125C	200MWF	75M	5P	250TP	1MA	ALN	MIT	BC184L	2N3707	0
25C871	NS	T092	L40	30V	25V	4V	30MA	125C	200MWF	75M	5P	350TP	1MA	ALN	MIT	BC184L	2N3707	0
25C872	NS	T05	L04	40V		3V	400MA	175C	3.5WC	400M		10MN	100MA	UMP		BFW47	2N3553	1
25C872M	NS	T039	L04	40V	20V	4V	400MA	175C	3.5WC	600M	3P5			UMP	FUJ	BFX33	2N3866	2
25C873	NS	T039	L04	75V		4V	1A	150C	500MWF	100M		30MN	50MA	RMG		BSW66	2N4001	1
25C874	NS	T039	L04	50V		4V	1A	150C	500MWF	100M		30MN	50MA	RMG		BSW66	2N4001	1
25C875	NS	T039	L04	75V	75V	4V	500MA	150C	500MWF	85M	10P	100TP	50MA	RMH	SAN	BSW54	2N2219A	0
25C876	NS	T039	L04	50V	50V	4V	500MA	150C	500MWF	85M	10P	100TP	50MA	RMG	SAN	BSW54	2N2219A	0
25C877	NS	T018	L01	40V		4V5	200MA	175C	300MWF			30MN	10MA	RLS		BSW64	2N2221A	1
25C878	NS	T018	L01	40V		4V5	200MA	175C	300MWF			35MN	10MA	VLS		BSX20	2N2369A	0
25C879	NS	T05	L04	60V	45V	5V	1A	175C	800MWF			40MN	100MA	RMS		BSS14	2N5859	1
25C880	NS	T05	L04	60V	45V	5V	1A	175C	800MWF			40MN	100MA	RMS		BSS14	2N5859	1
25C881	NS	T092	L21	60V	45V	5V	200MA	125C	400MWF	100M		30MN	150MA	RMG		BCW36	2N3704	1
25C882	NS	T03	L05	150V		5V	2A	150C	25WC	15M		20MN	500MA	RHE		BDY25		1
25C883	NS	T03	L05	90V		5V	2A	150C	25WC	15M		20MN	500MA	RHH		BDX11	2N3442	1
25C884	NS	T066	L43	80V		5V	2A	150C	15WC	15M		20MN	500MA	RHE		BDY78	2N6372	1
25C885	NS	T03	L05	330V		5V	7A	150C	50WC			15MN	1A	AHE		BDY28	2N6251	1
25C886	NS	T03	L05	270V		5V	7A	150C	50WC			15MN	1A	AHE		BDY28	2N6251	1
25C887	NS	T03	L05	210V		5V	7A	150C	50WC			15MN	1A	AHE		BDY28	2N6251	1
25C888	NS	T03	L05	150V		5V	7A	150C	50WC			15MN	1A	AHE		BDY28	2N6251	1
25C889	NS	T03	L05	90V		5V	7A	150C	50WC			15MN	1A	AHH		BDX11	2N3442	1
25C890	NS	T039	L04	40V	20V	3V	400MA	175C	4WC	600M		20MN	100MA	UMA	NIP			0
25C891	NS	X28	L65	40V	20V	4V	600MA	175C	10WC	300M		20MN	100MA	VHP	NIP			1
25C892	NS	X28	L65	40V	20V	4V	1A2	175C	18WC			20MN	300MA	VHP	NIP			1
25C893	NS	T037	L47	100V	60V	6V	300MA	175C	12WC	10M		50/370	50MA	RMH	FUJ	BDY78		0
25C894	NS	OBS	OBS	25V	12V	6V	100MA	200C	100MWF	100M		50MN	1MA	RLS	SOY	BSX20	2N2369	1
25C895	NS	X03	L05	380V	90V	8V	2500MA	150C	18WC	10M		20/350	100MA	RHE	SOY		2N3739	0
25C896	NS	T018	L01	55V	30V	5V	200MA	150C	300MWF	100M	7P	70TP	5MA	ALG	NIP	BC107	A157	0
25C897	NS	T03	L05	150V	100V	5V	7A	150C	60WC	5M		20MN	1A	RHE		BDY56	2N3448	1
25C898	NS	T03	L05	150V	100V	5V	7A	175C	80WC			25/200	1A	RHH	HIJ	BDY79	2N5050	0
25C899	NS	T092	L21	50V	25V	5V	30MA	125C	250MWF	75M		115TP	500UA	ALN	NIP	BC184L	2N3707	0
25C900	NS	T092	L21	30V	25V	5V	20MA	125C	250MWF	75M		250TP	500UA	ALN	NIP	BC184L	2N3707	0
25C901	NS	T03	L05	200V	200V	6V	5A	150C	50WC			14/25	5A	RHE	MAT	BU120		0
25C901A	NS	T03	L05	250V		6V	5A	150C	50WC			14/25	5A	RHE	MAT	BU120		0
25C902	NS	T03	L05	150V		6V	10A	175C	75WC			20MN	5A	AHE		BDY56	2N3442	1
25C903	NS	T092	L40	35V	30V	4V	300MA	125C	200MWF	75M	16P	100TP	150MA	AMG	MIT	BCW36	2N3704	0
25C904	NS	T092	L40	50V	45V	4V	300MA	125C	200MWF	75M	16P	100TP	150MA	AMG	MIT	BCW36	2N3704	0
25C905	NS	T092	L40	65V	60V	4V	300MA	125C	200MWF	75M	16P	100TP	150MA	AMG	MIT	BCW36	2N3704	0
25C906	NS	T05	L04	50V	30V	7V	500MA	175C	600MWF			60MN	10MA	RMS		BSW54	2N2219A	1
25C907	NS	T01	L02	40V	20V	5V	100MA	175C	200MWF	120M		100MN	10MA	RLS		BC108	2N930	1
25C908	NS	T05	L04	40V	24V	3V	500MA	175C	5WC	400M		5MN	100MA	VMG	MIT	BSW54	2N2219A	0
25C909	NS	X28	L65	40V	40V	3V	500MA	200C	7WC	400M		20MN	100MA	VHP	MIT			1
25C910	NS	X28	L65	40V	40V	3V	1A	200C	10WC			20MN	100MA	VHP	MIT			1
25C911	NS			40V	40V	3V	500MA	200C	2WF	400M		20MN	100MA	VHP	MIT			1
25C911A	NS	X62D	X62	40V		4V	500MA	175C	1.7WC	400M	6P	20/180	100MA	UMP	MIT	BLX66	2N5917	2
25C912	NS	T01	L02	30V	25V	4V	100MA	150C	150MWF	75M	5P	90TP	10MA	ALG	MIT	BC107	A157	0
25C913	NS	T018	L01	40V	35V	5V	300MA	175C	300MWF		5P	45MN	30MA	RMS	NIP	BSX20	2N2369	0
25C914	NS	T018	L01	40V	35V	5V	300MA	175C	300MWF		5P	45MN	30MA	RMS	NIP	BSX20	2N2369	0
25C915	NS	T018	L01	40V	35V	5V	300MA	175C	300MWF		5P	45MN	30MA	RMS	NIP	BSX20	2N2369	0
25C916	NS	T08	L12	100V	70V	6V	2A	175C	2WF	38P		40/120	400MA	RHH	NIP		2N2782	0
25C917	NS	T01	L02	40V	40V	3V	50MA	175C	300MWF	90M	2P	8MN	10MA	RLG	HIJ	BFX73	2N918	0
25C918	NS	T072	L06	20V	20V	3V	30MA	175C	375MWF	200M	OR9	20MN	4MA	FRM	SOY	BF185		0
25C920	NS	X37		50V	25V	5V	30MA	150C	150MWF	125M		30MN	300UA	ALN	NIP	BC109C	2N930	1
25C921	NS	X37		25V	12V	2V	10MA	150C	100MWF	300M		30MN	500UA	ALN	NIP			1
25C922	NS	T092	L21	30V	25V	5V	20MA	125C	250MWF			250TP	500UA	ALN	NIP	BC184L	2N3707	0
25C924	NS	T092	L21	30V	15V	5V	20MA	125C	250MWF			100TP	500UA	ALG	NIP	BC182L	2N3710	0
25C925	NS	T092	L21	30V	15V	5V	50MA	125C	250MWF	125M		50MN	500UA	RLG		BC184L	2N3707	1
25C926	NS	X20	L42	115V	115V	3V5	100MA	125C	100MWF	80M	4P5	50TP	1MA	ALH	SOY	BSX21	2N1990R	0
25C926A	NS	X20	L42	210V	210V	5V	30MA	120C	320MWF	55M	4P	30/276	1MA	ALE	SOY	BF347	2N5058	2
25C927	NS	T072	L06	30V	15V	3V	20MA	125C	150MWF	250M	2P	80TP	1MA	VLA	SAN	BFX73	2N918	0
25C928	NS	T072	L06	30V	15V	3V	20MA	125C	150MWF	250M	2P	80TP	1MA	VLA	SAN	BFX73	2N918	0
25C929	NS	T092	L21	15V	10V	5V	30MA	125C	120MWF	150M	3P5	100TP	1MA	VLA	SAN	BFX73	2N918	0