

2 SD 720	Mit	Si-N-Darl	S P, 400/400V, 7A, 100W, hFE=400...1500	23a	TO-3				BU 322(A), BUX 29, 2SD707, 2SD796, ++
2 SD 721	Sak	Si-N-Darl	P, 100/80V, 6/10A, 50W, hFE=1000, -/16,5µs	{2SB711 17}	TO-220	BD 901	17j		BD 649, BD 901, BDW 73C, BDX 53C, ++
2 SD 722	Sak	Si-N-Darl	=2SD721: 120/100V	{2SB712 17}	TO-220	(BD 901)7	17j		BD 651, BDT 21, BDW 73D, BDX 53E, ++
2 SD 723	Hit	Si-N	P, 100/100V, 4A, 40W	17j	TO-220	BD 243 C	17j		BD 243C, BD 539C, BD 953, 2SD712, ++
2 SD 724	Hit	Si-N	P, 200/80V, 4A, 30W	17j	TO-220				BD 243F, 2SC2767, 2SD772A,B
2 SD 725	Hit	Si-N	TV-HA, 1500/600V, 6A, 50W, sat<5V(5A)	23a	TO-3	2SD725	23a		2SC2027
2 SD 726	Hit	Si-N	P, 100/80V, 4/8A, 40W, 10MHz	{2SB690 17}	TO-220	BD 243 C	17j		BD 243C, BD 539C, BD 953, 2SD712, ++
2 SD 727	Mat	Si-N	P, 130/80V, 5/8A, 60W, 7MHz	{2SB891 18}	TO-3P	2SC2837	18j		BD 245D, 2SD731, 2SD751, 2SD1046, ++
2 SD 728	Mat	Si-N	=2SD727: 150/100V, 6/10A, 70W	{2SB692 18}	TO-3P	2SC2837	18j		BD 245D, 2SC3263, 2SD731, 2SD751, ++
2 SD 729	Hit	Si-N-Darl+Di	100/100V, 20/30A, 125W, hFE=1k...20k, 2/8µs	{2SB693 23a}	TO-3				BDX 69B, MJ 11014, 2N6284
2 SD 730	Hit	Si-N-Darl+Di	=2SD729: 25/40A	23a	TO-3				BDX 69B, MJ 11014, MJ 11016
2 SD 731	Mat	Si-N	P, 170/120V, 7/12A, 80W, 7MHz	{2SB695 18}	TO-3P	2SC2837	18j		BD 245E, 2SC3263, 2SD751
2 SD 732(K)	Say	Si-N	P, 150/120K=150/140)V, 8/12A, 80W, 15MHz	{2SB696 23a}	TO-3	2SC3263	18j		BD 245D, 2SC2837, 2SD551, 2SD752, ++
2 SD 733	Say	Si-N	P, 160/140V, 12/20A, 100W, 15MHz	{2SB697 23a}	TO-3	MJ 15015	23a		BD 745E, MJ 15015, 2SC2607...08, ++
2 SD 733 K		Si-N	=2SD733: 180/160V	23a	TO-3	MJ 15015	23a		BD 757F, MJ 15015, 2SC2607...08, ++
2 SD 734	Say	Si-N	Uni, 25/20V, 0,7/1,5A, 0,6W, 250MHz, sat<0,3V(0,5A)	7c	TO-92	2SD1207	7c		2SC4483, 2SD1207, 2SD1302, 2SD1616, ++
				{2SB698					
2 SD 735	Hit	Si-N	P, 160/120V, 12/15A, 100W	{2SB699 20j}		2SC3264	20j		2SC2526, 2SC2565, 2SC2766(A), 2SC2921, ++
2 SD 736(A)	Hit	Si-N	=2SD735: 160/140V	{2SB700 20j}		2SC3264	20j		2SC2526, 2SC2565, 2SC2766(A), 2SC2921, ++
2 SD 737	Hit	Si-N	P, 160/160V, 12A, 120W	20j		2SC3264	20j		2SC2526, 2SC2565, 2SC2766(A), 2SC2921, ++
2 SD 738(A)	Hit	Si-N	P, 160/160V, 12/15A, 125W, 10(A=25)MHz	{2SB702 20j}		2SC3264	20j		2SC2526, 2SC2565, 2SC2766(A), 2SC2921, ++
2 SD 741	Nec	Si-N	HF.LFS P, 40/20V, 5/8A, 15W, 200MHz, 1,5/0,4µs	14h	TO-126	(2SC3420)	14b		MJE 200, 2SC2270, 2SC2594, 2SD2147
2 SD 743(A)	Nec	Si-N	LF P.TV, 100/80V, 4/6A, 40W, 17MHz	{2SB703 17}	TO-220	BD 243 C	17j		BD 243C, BD 539C, BD 953, 2SD726, ++
2 SD 745	Nec	Si-N	P, 140/140V, 10/15A, 120W, 15MHz	{2SB705 20j}		2SC3264	20j		2SC2564...2565, 2SC2838, 2SD845, ++
2 SD 745 A		Si-N	=2SD745: 150/150V	20j		2SC3264	20j		2SC2526, 2SC2565, 2SC2838, 2SD845, ++
2 SD 745 B		Si-N	=2SD745: 160/160V	20j		2SC3264	20j		2SC2526, 2SC2565, 2SC2766(A), 2SC2921, ++
2 SD 746	Nec	Si-N	P, 180/180V, 10/15A, 200W, 15MHz	{2SB706 4-SILP	(CBEC)				
2 SD 746 A		Si-N	=2SD746: 220/220V	4-SILP	(CBEC)				
2 SD 747	Mit	Si-N	S, 50/30V, 0,5A, 1W(Tc=25°), <1µs	2a	TO-18	(BC 337)	7a		BSW 61...64, BSX 33, 2N2221...2222(A), ++
2 SD 748	Hit	Si-N	S P, 250/200V, 3A, 80W	23a	TO-3	(BU 608)	23a		TIP 51...54, 2SC1463, 2SD632
2 SD 748 A		Si-N	=2SD748: 250/250V	23a	TO-3	(BU 608)	23a		TIP 51...54, 2SC1463, 2SD632
2 SD 749	Mat	Si-N	S P, 750/300V, 3A, 50W	23a	TO-3	BUW 11 A	18j		BUW 11(A), BUX 46(A), 2SC3088, 2SC3448++
2 SD 750	Mat	Si-N	P, 110/80V, 15A, 100W, 1MHz	23a	TO-3	2N3055	23a		BD 317, BD 745C, 2N3055, 2N5629...31, ++
2 SD 751	Mat	Si-N	P, 200/140V, 9/15A, 100W, 7MHz	{2SB713 18}	TO-3P	2SC3263	18j		BD 245F, 2SC3263
2 SD 752	Hit	Si-N	P, 160/160V, 15/20A, 150W	{2SB722 23a}	TO-3	MJ 15015	23a		BDW 12, MJ 15015, 2N3773, 2SC2607...08, ++
2 SD 753	Hit	Si-N	=2SD752: 200/200V	{2SB723 23a}	TO-3	MJ 15015	23a		BDW 16, MJ 15015, 2SC1585, 2SC2607...08, ++
2 SD 754	Hit	Si-N	Uni, 25/20V, 0,7/1A, 0,625W, 280MHz	{2SB721 7e}	TO-92	BC 337 ⁸	7a		(BC 337...338, BC 635, BC 637, BC 639, ++) ⁸
2 SD 755	Hit	Si-N	Uni, 100/100V, 0,05A, 0,75W, 350MHz	{2SB715 7c(9mm)}	TO-92L	2SC2632	7c(9mm)		2SC2632, 2SC3245(A), 2SC3248, 2SD3800
2 SD 756	Hit	Si-N	=2SD755: 120/120V	{2SB716 7c(9mm)}	TO-92L	2SC2632	7c(9mm)		2SC2632, 2SC3245(A), 2SC3248, 2SC3800
2 SD 756 A		Si-N	=2SD755: 140/140V	7c(9mm)	TO-92L	2SC2632	7c(9mm)		2SC2375, 2SC2631...32, 2SC3248, 2SC3245A, ++
2 SD 757	Hit	Si-N	LFS/Vid P, 160/160V, 0,05A, 140MHz	{2SB717 17}	=TO-220	(BF 471) ⁴	14h		2SC3514, (BF415, BF417, BF469, BF471, ++) ⁴
2 SD 758	Hit	Si-N	=2SD757: 200/200V	{2SB718 17}	=TO-220	(BF 471) ⁴	14h		2SC1819, (BF415, BF417, BF469, BF471, ++) ⁴
2 SD 759	Hit	Si-N	P, 160/160V, 2/4A, 25W, 100MHz	{2SB719 17}	TO-220	(2SD1138) ⁸	17j		2SC2529, 2SC2660
2 SD 760	Hit	Si-N	=2SD759: 200/200V	{2SB720 17}	TO-220	(2SD1138) ⁸	17j		2SC2660
2 SD 761	Say	Si-N	P, 180/180V, 1,5/3A, 20W, 6MHz	17j	TO-220	2SD1138	17j		BD 239E, 2SD608A, 2SD610, 2SD1138, ++
2 SD 762	Mat	Si-N	P, 60/60V, 3/4A, 25W	{2SB724 17}	TO-220	BD 243 C	17j		BD 241A, BD 535, BD 539A, BD 953, ++
2 SD 762 A		Si-N	=2SD762: 80/80V, 4A, 30W	17j	TO-220	BD 243 C	17j		BD 243B, BD 537, BD 539B, BD 951, ++
2 SD 763	Hit	Si-N	Uni, TV-HA, 120/60V, 1/1,5A, 0,9W, sat<0,5V(1A)	7c(9mm)	TO-92L	(2SD1812)	7c(9mm)		(2SC2383, 2SC3228, 2SD667(A), 2SD1812)
2 SD 764	Hit	Si-N	TV-HA, 1500/600V, 1,5A, 50W, sat<1,5V(1A)	23a	TO-3	(BU 208 A)	23a		BU 205...206, 2SC1922, 2SD818...819, ++
2 SD 765	Hit	Si-N	TV-HA, 1500/800V, 3A, 50W, sat<5V(2,5A)	23a	TO-3	BU 208 A	23a		BU 207...209(A), BU 508(A), 2SC3023...24, ++
2 SD 766	Mat	Si-N	S P, LF Out, 300V, 0,7/2,5A, 30W, 45MHz	22a	TO-66	(BUX 85)	17j		BUW 40(A), TIP 47...50, 2SC782, ++
2 SD 767	Mat	Si-N	Uni, 60/60V, 0,1A, 0,25W, 150MHz, Ur=0,3V	{2SB725 7c}	TO-92	BC 546	7a		BC 174, BC 182, BC 190, BC 546, ++
2 SD 768(K)	Hit	Si-N-Darl+Di	P, 120/120V, 6/10A, 40W, hFE=1k...20k, 1/3µs	{2SB727 17}	TO-220	2SD1756 ⁷	17j		BD 651, BDW 63D, BDW73D, BDT 21
2 SD 769	Mat	Si-N	Uni, 20/15V, 0,5A, 0,4W	7c	TO-92	BC 639	7c		BC 337...338, BC 635, BC 637, BC 639, ++
2 SD 770	Mat	Si-N	=2SD769: 50/40V	7c	TO-92	BC 639	7c		BC 337, BC 635, BC 637, BC 639, ++
2 SD 771	Mat	Si-N	Uni, 25/25V, 0,05A, 0,15W, F=6dB(1kHz)	7c	TO-92	BC 546	7a		BC 168, BC 183, BC 238, BC 548, ++
2 SD 772	Mat	Si-N	P, 150/80V, 5A, 40W, 40MHz	17j	TO-220	(BU 406)	17j		MJE 15030
2 SD 772 A		Si-N	=2SD772: 200V	17j	TO-220	(BU 406)	17j		
2 SD 772 B		Si-N	=2SD772: 250V	17j	TO-220	(BU 406)	17j		
2 SD 773	Nec	Si-N	LF, 20/16V, 2A, 1W, 110MHz	{2SB733 9b}		2SC3225	7c(9mm)		2SC3225, 2SC4484, 2SD1246...47
2 SD 774	Nec	Si-N	Uni, 100/50V, 1A, 1W, 95MHz	{2SB734 9b}		2SD774	9b		2SD1616A, 2SD1768, 2SD1857, (BC 639) ¹³
2 SD 776	Tos	Si-N	S P, 200/180V, 5A, 100W, hi-hFE=500...2000	23a	TO-3				2SD1090
2 SD 777	Tos	Si-N	TV Reg. int. Z-Diode(C • B, 55V), 55/55V, 4/20A 100W, hi-hFE=500...2500	23a	TO-3				
2 SD 778	Mat	Si-N	Uni, 30/25V, 0,1A, 0,4W	9c		BC 546	7a		BC 168, BC 183, BC 238, BC 548, ++
2 SD 779	Mat	Si-N	=2SD778: 60/50V	9c		BC 546	7a		BC 174, BC 182, BC 190, BC 546, ++
2 SD 780	Nec	Si-N	SMD, Uni, 60/50V, 0,3A, 140MHz	{2SB736 35a}	SOT-23	BC 817	35a		BCW 65...66
2 SD 780 A		Si-N	=2SD780: 80/80V	35a	SOT-23				BCW 66
2 SD 781	Hit	Si-N	S P, TV-HA, 150/60V, 2/2,5A, sat<0,6V(1,5A)	14h	TO-126				2SD975
2 SD 782	Hit	Si-N	TV-HA, 300/80V, 5A, 30W	17j	TO-220	BU 406	17j		BU 406...408, 2SD884...885, 2SD1150, ++
2 SD 783	Hit	Si-N	TV-HA, 1500/600V, 4A, 50W, sat<5V(3,5A)	23a	TO-3	BU 208 A	23a		BU 208...209(A), BU 508(A), 2SC2928, ++
2 SD 784	Hit	Si-N	=2SD783: 1700/700V, 5A, sat<5V(4,5A)	23a	TO-3	2SC3026	23a		BU 209(A), 2SC3026
2 SD 785	Hit	Si-N	=2SD783: 1900/700V, 5A	23a	TO-3	(BU 209) ⁷	23a		2SC2125
2 SD 786(S)	Rhm	Si-N	LF, in, 50/40V, 0,3A, 0,25W, 100MHz	{2SB737 7c, 41c}	TO-92, -	BC 550	7a		BC 184, BC 413...414, BC 550, 2SC2390, ++
2 SD 787	Hit	Si-N	LF Out, 20/16V, 2A, 0,9W, 100MHz	{2SB738 7c(9mm)}	TO-92L	2SD1207	7c(9mm)		2SD1100, 2SD1014, 2SD1146, 2SD1207, ++
2 SD 788	Hit	Si-N	=2SD787: 20/20V	{2SB739 7c(9mm)}	TO-92L	2SD1207	7c(9mm)		2SD1100, 2SD1014, 2SD1146, 2SD1207, ++
2 SD 789	Hit	Si-N	LF Out, 100/50V, 1A, 0,9W, 100MHz	{2SB740 7c(9mm)}	TO-92L	2SD1812	7c(9mm)		2SC2383, 2SC3228, 2SD667(A), 2SD1812, ++
2 SD 790	Hit	Si-N	=2SD789: 100/70V	{2SB741 7c(9mm)}	TO-92L	2SD1812	7c(9mm)		2SC2383, 2SC3228, 2SD667(A), 2SD1812, ++
2 SD 792	Mat	Si-N	TV-HA, 1500/700V, 5A, 35W(Tc=90°), sat<1,5V(4,5A)	23a	TO-3	BU 208 A	23a		BU 208(A), BU 508(A), 2SC2928, 2SD954, ++
2 SD 793	Nec	Si-N	P, 40/30V, 3A, 10W, 65MHz	{2SB743 14h}	TO-126	2SD1348	14h		BD 785, MJE 240...244, 2SD1348
2 SD 794(A)	Nec	Si-N	P, 70/45(A=70/60)V, 3/5A, 10W, 60MHz	{2SB744 14h}	TO-126	(BD 189) ⁸	14h		BD 787, BD 789, MJE 240...244
2 SD 795(A)	Nec	Si-N	P, 50/40(A=50/50)V, 3/6A, 20W, 95MHz, sat<0,7V(2A)	17j	TO-220	(BD 243 C) ⁸	17j		2SC3252, 2SC3258
2 SD 796	Fjd	Si-N-Darl	S P, 500/450V, 8A, 100W, hFE>200, <1,4/21µs	23a	TO-3				BU 922, BUW 81(A), 2SD707, 2SD685, ++
2 SD 797	Tos	Si-N	S P, 100/80V, 30A, 200W, 3MHz, 1,5/7µs	23a	TO-3				BDW 30, BDU 29, MJ 802
2 SD 798	Tos	Si-N-Darl	S P, 600/300V, 6A, 30W, hFE>1500, 1/13µs	17j	TO-220	2SC798	17j		BU 810, 2SC3579
2 SD 799	Tos	Si-N-Darl+Di	S P, 600/400V, 6A, 30W, hFE>600, 1/13µs	17j	TO-220	2SD798	17j		BU 810, 2SC3579
2 SD 800	Hit	Si-N	S P, 750/300V, 4A, 30W, 8MHz, -/1350ns	23a	TO-3	BUW 11 A	18j		BUS 11(A), BUW 11(A), BUX 82...83, ++
2 SD 801	Hit	Si-N	S P, TV-SN, 800/375V, 6A, 50W	23a	TO-3	BU 426 A	18j		BU 326(A), BU 426(A), BU 526, 2SD1093
2 SD 802	Hit	Si-N	=2SD801: 900/400V	23a	TO-3	BU 426 A	18j		BU 326A, BU 426A, BU 526, 2SD1093
2 SD 803	Mat	Si-N-Darl+Di	P, 120/100V, 8A, 100W, hFE>2000	23a	TO-3				BDV 65C, BDX 63C, 2SD922, 2SD1210
2 SD 804	Mat	Si-N	P, 60/60V, 3A, 25W	17j	TO-220	BD 243 C	17j		BD 241A, BD 535, BD 539A, BD 935, ++
2 SD 805	Fjd	Si-N-Darl	S P, 600/600V, 30A, 200W, hFE>100, <3/16µs	68a					
2 SD 806	Fjd	Si-N-Darl	=2SD805: 50A, 400W	=74					