

2 SK 147	Tos	N-FET	Uni In, 40V, Idss=5...30mA, Up=0.3...1.2V	{2SJ72	7a(9mm)	TO-92L	2N5247, 2SK130, 2SK151, 2SK162, 2SK363
2 SK 148	Mat	N-FET	FM/VHF, 25V, 10mA, Idss<12mA, F=2.5dB(100MHz)		9e		
2 SK 149	Nec	N-FET	UHF, 20V, 35mA, Idss=8...32mA, Up=0.35...2.2V F=2/Gp=12dB(400MHz)		5m	TO-72	
2 SK 150	Tos	N-FET	Dual, 50V, Idss=1...14mA, Up=0.3...2V		7-SIP	(DGSSSGD)	
2 SK 151	Hit	N-FET	S, LF In, 40V, 200mA, Idss=6...50mA, Up<1.1V	{2SJ51	7a(9mm)	TO-92L	2N5247
2 SK 152	Son	N-FET	FM/VHF, 15V, 50mA, Idss=9.5...42mA, Up=0.55...2V		7d	TO-92	BF 410D
2 SK 154	Mat	N-FET	FM/VHF, 20V, 30mA, Idss<18mA, F=1.5dB(100MHz)		7f	TO-92	
2 SK 155	Mat	N-FET	Uni In, 20V, 30mA, Idss=0.5...30mA, Up=0.1...1.5V		7a	TO-92	2SK68, 2SK106, 2SK184
2 SK 156	Say	N-FET	LF(Mic) Inp, 20V, Idss=0.06...0.8mA, Zin>20MΩ		41e		
2 SK 157	Hit	N-FET	SMD, 50V, 20mA, Idss=0.5...12mA, Up=0.13...1.5V		35f	SOT-23	2SK94
2 SK 158	Mat	N-FET	SMD, 55V, Idss<6.5mA, F<5dB(120Hz)		35b	SOT-23	
2 SK 160	Nec	N-FET	SMD, VHF, 30V, 20mA, Idss=0.5...12mA, Up=0.25...4.5V		35f	SOT-23	
2 SK 160 A		N-FET	=2SK160: 50V		35f	SOT-23	
2 SK 161	Tos	N-FET	FM/VHF, 18V, Idss=1...10mA, Up=0.4...4V F<3.5/Gp=18dB(100MHz)		41d		2N5246, 2SK107
2 SK 162	Nec	N-FET	LF In, MC Inp, 40V, Idss=5...30mA, Up<1.2V		7a	TO-92	2SK147, 2SK151
2 SK 163	Nec	N-FET	Uni, In, 50V, 30mA, Idss=1...18mA, Up=0.2...1.2V		7a	TO-92	2SK43, 2SK121, 2SK170, 2SK186...187, ++
2 SK 165	Mat	N-FET	Video-Camera, 15V, 50mA, Idss=8...32mA, Up<3V		7e, 7d	TO-92	
2 SK 168	Hit	N-FET	FM Inp, Mx, Os, 20mA, 30V, Idss=4...20mA, Up<3V F=1.7/Gp=27dB(100MHz)		7f	TO-92	BF 410C
2 SK 169	Mat	N-FET	LF In, 15V, 50mA, Idss<50mA		7	TO-92	
2 SK 170	Tos	N-FET	Uni In, 40V, Idss=1...20mA, Up=0.2...1.5V	{2SJ74	7a	TO-92	2SK43, 2SK121, 2SK163, 2SK186...187, ++
2 SK 171	Hit	N-FET	Dual, 20V, 80mA, Idss=5...60mA, Up<2V, F<1dB(100Hz)		7-SIP	(DGSSSGD)	
2 SK 173	Son	MOS-N-FET-e	VFET, 210/8V, 10A, 95W		23e	TO-3	(BUZ 35, 2SK401) ⁵
2 SK 175	Hit	MOS-N-FET-e	VFET, 180/20V, 8A, 125W, on<1.7Ω, 250/90ns	{2SJ55	23e	TO-3	2SK258, (BUZ 33) ⁵
2 SK 176	Hit	MOS-N-FET-e	=2SK175: 200/20V	{2SJ56	23e	TO-3	2SK258, (BUZ 33) ⁵
2 SK 180	old	MOS-N-FET-e	VFET, 600V, 20A, 300W, on<1.5Ω, 200/250ns		68e		
2 SK 181	old	MOS-N-FET-e	=2SK180: 800V		68e		
2 SK 182	old	MOS-N-FET-e	VFET, 600V, 60A, 1000W, on<0.66Ω, 250/300ns				
2 SK 183	old	MOS-N-FET-e	=2SK182: 800V				
2 SK 184	Tos	N-FET	LF In, 50V, Idss=0.6...14mA, Up=0.2...1.5V		41a		2SK68, 2SK106
2 SK 185	Son	N-FET	Dual, 30V, 20mA, Idss=0.9...14.3mA, Up=0.18...1.49V		7e + 7a	2x =TO-92	
2 SK 186	Hit	N-FET	Uni In, 40V, 30mA, Idss=1.6...12mA, Up=0.13...1.5V		7a	TO-92	2SK187, 2SK364, 2SK366
2 SK 187	Hit	N-FET	Uni In, 40V, 30mA, Idss=2.5...20mA, Up=0.13...1.5V =2SK190		7a	TO-92	2SK186, 2SK364, 2SK366
2 SK 190	Hit	N-FET	LF In, 40V, 0.2A, Idss=6...50mA, Up=0.13...1.5V		7a(9mm)	TO-92L	
2 SK 191	Hit	N-FET	LF, 15V, 0.5A, Idss=10...200mA, Up<3V, F=1,1dB(1k)		7a(9mm)	TO-92L	
2 SK 192(A)	Tos	N-FET	FM/VHF, 18V, Idss=3...24mA, Up=1.2...3V F<3.5/Gp=20dB(100MHz), A: Gp=24dB(100MHz)		41d		BF 410B...C
2 SK 193	Nec	N-FET	FM Tuner, 20V, 10mA, Idss=0.5...8mA, Up<2.5V F<6/Gp=21dB(100MHz)		40f	(SST)	BF 410A, 2SK195, 2SK212
2 SK 194	Nec	N-FET	Dual, 40V, 50mA, Idss=5...24mA, Up<1.2V		7e + 7a	2x =TO-92	
2 SK 195	Nec	N-FET	FM Tuner, 20V, 10mA, Idss=0.5...8mA, Up<2.5V F<6/Gp=21dB(100MHz)		7f	TO-92	BF 410A, 2SK193, 2SK212, 2SK606
2 SK 196	Hit	MOS-N-FET-e	VFET, 160/15V, 0.5A, 0.8W, on<15Ω, 20/30ns		2e(S=case)	TO-39	BSS 93
2 SK 197	Hit	N-FET	SMD, VHF, 18V, 20mA, Idss=2...14mA, Up=0.3...4V		35c	SOT-23	2SK210, 2SK217
2 SK 198	Mat	N-FET	SMD, LF In, 30V, 20mA, Idss=0.5...12mA, Up=0.1...1.5V		35f	SOT-23	
2 SK 199	Mat	N-FET	SMD, HF, 15V, Idss<12mA		35c	SOT-23	
2 SK 201	Nec	GaAs-N-FET	UHF, C...X-Band, 10V, 400mA, Idss=180...400mA Up=3...7V, F=3/Gp=9dB(8GHz)		52(SGSD)	SOT-100	
2 SK 203	Nec	GaAs-N-FET	UHF, C...X-Band, 10V, 180mA, Idss=90...180 Up=3...7V, F=2.6/Gp=11dB(8GHz)		52(SGSD)	SOT-100	
2 SK 208	Tos	N-FET	SMD, C-Mic, 50V, Idss=0.3...6.5mA, Up=0.4...5V		35f	SOT-23	
2 SK 209	Tos	N-FET	SMD, Uni, 50V, Idss=0.6...14mA, Up=0.2...1.5V		35f	SOT-23	2SK94, 2SK425
2 SK 210	Tos	N-FET	SMD, FM/VHF, 18V, Idss=3...24mA, Up=1.2...3V F<3.5/Gp=24dB(100MHz)		35c	SOT-23	2SK217
2 SK 211	Tos	N-FET	SMD, FM/VHF, 18V, Idss=1...10mA, Up=0.4...4V F<3.5/Gp=18dB(100MHz)		35c	SOT-23	2SK197
2 SK 212	Say	N-FET	FM, 20V, 20mA, Idss=0.6...12mA, Up<2.5V F<6/Gp=21dB(100MHz)		41d		BF 410A, 2N5484
2 SK 213	Hit	MOS-N-FET-e*	VFET, 140/15V, 0.5A, 30W, on=8Ω, 20/30ns	{2SJ76	17d	TO-220	
2 SK 214	Hit	MOS-N-FET-e*	=2SK213: 160/15V	{2SJ77	17d	TO-220	
2 SK 215	Hit	MOS-N-FET-e*	=2SK213: 180/15V	{2SJ78	17d	TO-220	
2 SK 216	Hit	MOS-N-FET-e*	=2SK213: 200/15V	{2SJ79	17d	TO-220	
2 SK 217	Hit	N-FET	SMD, VHF, 30V, 20mA, Idss=5...12mA, Up<2.5V		35c	SOT-23	2SK210, 2SK217
2 SK 218	Mat	N-FET	Video-Camera, 15V, 50mA, Idss=5...42mA, Up<3V		7d	TO-92	
2 SK 220	Hit	MOS-N-FET-e	VFET, 160/20V, 8A, 100W, on<1.5Ω, 25/45ns		23e	TO-3	2SK258, (BUZ 33) ⁵
2 SK 221	Hit	MOS-N-FET-e	=2SK220: 200V		23e	TO-3	2SK258, (BUZ 33) ⁵
2 SK 222	Say	N-FET	Uni, In, 40V, Idss=0.6...12mA, Up=0.5V, F<3dB(1kHz)		7e	TO-92	2SK68, 2SK102, 2SK184
2 SK 223	Say	N-FET	LF Drv, 80V, Idss=1.2...24mA, Up=0.75V		7e	TO-92	
2 SK 225	Hit	MOS-N-FET-e	VFET, 120/15V, 7A, 100W, on<1.7Ω, 180/60ns	{2SJ81	20d		(2SK343...344) ⁵
2 SK 226	Hit	MOS-N-FET-e	=2SK225: 140/15V	{2SJ82	20d		(2SK343...344) ⁵
2 SK 227	Hit	MOS-N-FET-e	=2SK225: 160/15V	{2SJ83	20d		(2SK344) ⁵
2 SK 238	Nec	N-FET	SMD, FM, 20V, Idss=0.5...12mA, Up<2.5V Gp=21dB(100MHz)		35e	SOT-23	BF 510
2 SK 240	Tos	N-FET	Dual, 40V, Idss=2.6...20mA, Up=0.2...1.5V, F<2dB(1k)		7e + 7a	2x =TO-92	
2 SK 241	Tos	MOS-N-FET-e*	FM/VHF, 20V, 30mA, Idss=1.5...14mA, Up<2.5V F=1.7<3/Gp=28dB(100MHz)		41d		
2 SK 242	Say	N-FET	=2SK212: SMD		35e	SOT-23	BF 510, 2SK238
2 SK 246	Tos	N-FET	Uni, 50V, Idss=1.2...14mA, Up=0.7...6V	{2SJ103	7e	TO-92	2N5457, 2SK330
2 SK 247	Mat	N-FET	SMD, HF, 15V, 200mA, Idss=0.5...12mA, Up<3V		35f	SOT-23	
2 SK 258	Hit	MOS-N-FET-e	VFET, 250/20V, 8A, 125W, on<1.3Ω, 25/140ns		23e	TO-3	(2SK277...278, 2SK293, 2SK299) ⁵
2 SK 259	Hit	MOS-N-FET-e	VFET, 350/20V, 5A, 125W, on<3Ω, 25/140ns		23e	TO-3	(BUZ 44, BUZ 46, BUZ 63) ⁵
2 SK 260	Hit	MOS-N-FET-e	VFET, 400/20V, 5A, 125W, on<3Ω, 25/140ns		23e	TO-3	(BUZ 44, BUZ 46, BUZ 63) ⁵
2 SK 261	Hit	N-FET	=2SK213				→2SK213
2 SK 262	Hit	N-FET	=2SK213				→2SK213
2 SK 263	Hit	N-FET	=2SK213				→2SK213
2 SK 264	Hit	N-FET	=2SK214				→2SK214
2 SK 266	Tos	N-FET	LF(Mic) Inp 15V, Zin>200MΩ				
2 SK 270	Tos	N-FET	Dual, 40V, Idss=1...20mA, Up=0.2...2V, F<2dB(1kHz)		7-SIP	(DGSSSGD)	
2 SK 271	Tos	MOS-N-FET-e	VFET, 140/8V, 8A, 120W	{2SJ91	23a	TO-3	2SK405, 2SK631, 2SK633, 2SK1529
2 SK 272	Tos	MOS-N-FET-e	=2SK271: 7A, 100W	{2SJ92	18p	TO-3P	2SK413...414, 2SK631, 2SK633, 2SK1529