

2 SJ 348	Say	MOS-P-FET-e	VFET, LogL, 60/20V, 30/120A, 70W, on<0.04Ω	17p	TO-220	2SJ292
2 SJ 349	Tos	MOS-P-FET-e*	VFET, LogL, 60/20V, 20A, 35W, <45mΩ(10A), 35/120ns	17c	TO-220 Iso	2SJ177, 2SJ294, 2SJ322, 2SJ330, 2SJ374
2 SJ 350	Hit	MOS-P-FET-e*	VFET, LogL, 120/20V, 6/12A, 20W, <0.7Ω(4A), 56/250ns	17c	SOT-186	-
2 SJ 351	Hit	MOS-P-FET-e*	VFET, LF Out, 180/20V, 8A, 100W, 250/90ns	(2SK2220) 18d	TO-3P	-
2 SJ 352	Hit	MOS-P-FET-e*	=2SJ351: 200/20V	(2SK2221) 18d	TO-3P	-
2 SJ 353	Nec	MOS-P-FET-e*	VFET, LogL, 60/20V, ±1,5/3A, 1W, on<0,7Ω(1A)	9c	(SP-8)	-
2 SJ 355	Nec	MOS-P-FET-e*	SMD, VFET, LogL, 30/20V, ±2/4A, on<0,35Ω(1A)	39b	SOT-89	2SJ356, 2SJ363
2 SJ 356	Nec	MOS-P-FET-e*	SMD, VFET, LogL, 60/20V, ±2/4A, on<0,5Ω(1A)	39b	SOT-89	-
2 SJ 357	Nec	MOS-P-FET-e*	SMD, VFET, LogL, 30/20V, ±3/6A, on<0,2Ω(1,5A)	39b	SOT-89	2SJ358
2 SJ 358	Nec	MOS-P-FET-e*	SMD, VFET, LogL, 60/20V, ±3/6A, on<0,3Ω(1,5A)	39b	SOT-89	-
2 SJ 359	Tos	MOS-P-FET-e	VFET, LogL, 60/20V, 5A, on<0,25Ω(2,5A), 130/200ns	≈12	SOT-89	(2SJ266) ⁴
2 SJ 360	Tos	MOS-P-FET-e	SMD, VFET, LogL, 60/20V, 1A, <0,73Ω(0,5A), 20/100ns	39b	SOT-89	2SJ190, 2SJ278
2 SJ 361	Hit	MOS-P-FET-e*	SMD, VFET, LogL, 20/20V, 2/4A, on<0,4Ω(1A), 2/14μs integr. R-Gate	39b	SOT-89	-
2 SJ 362	Say	MOS-P-FET-e	VFET, LogL, 60V, 2A, 20W, on<0,4Ω	30p	TO-251	2SJ191, 2SJ194, 2SJ326
2 SJ 363	Hit	MOS-P-FET-e*	SMD, VFET, LogL, 30/20V, 2/4A, on<0,45Ω(1A)	39b	SOT-89	2SJ355...356
2 SJ 365	Shi	MOS-P-FET-e	VFET, 60/20V, 2A, 10W, <0,45Ω, 60/160ns	(2SK2279) 30p	TO-251,252	2SJ191, 2SJ223, 2SJ326
2 SJ 366	Shi	MOS-P-FET-e	VFET, 60/20V, 5A, 15W, <0,25Ω, 70/270ns	30p	TO-251,252	2SJ192, 2SJ245, 2SJ279, 2SJ327
2 SJ 367	Shi	MOS-P-FET-e	VFET, 60/20V, 5A, 15W, <0,25Ω, 70/270ns	30p	(TO-220MF)	2SJ214, 2SJ275
2 SJ 368	Shi	MOS-P-FET-e	=2SJ367: 20W	17c	TO-220 Iso	2SJ248, 2SJ263
2 SJ 369	Shi	MOS-P-FET-e	VFET, 60/20V, 10A, 40W, <0,16Ω, 100/320ns	30p	(TO-220MF)	2SJ214, 2SJ219, 2SJ296
2 SJ 370	Shi	MOS-P-FET-e	=2SJ369: 25W	17c	TO-220 Iso	2SJ236, 2SJ293, 2SJ321, 2SJ390
2 SJ 371	Shi	MOS-P-FET-e	VFET, 60/20V, 15A, 50W, <0,1Ω, 130/460ns	(2SK2284) 30p	(TO-220MF)	2SJ219, 2SJ288, 2SJ296, 2SJ384
2 SJ 372	Shi	MOS-P-FET-e	=2SJ371:	(2SK2285) 17c	TO-220 Iso	2SJ237, 2SJ265, 2SJ293, 2SJ321, 2SJ329
2 SJ 373	Shi	MOS-P-FET-e	VFET, 60/20V, 20A, 60W, <0,07Ω, 175/660ns	(2SK2286) 30p	(TO-220MF)	2SJ220, 2SJ297, 2SJ409
2 SJ 374	Shi	MOS-P-FET-e	=2SJ373:	(2SK2287) 17c	TO-220 Iso	2SJ294, 2SJ322, 2SJ330, 2SJ374
2 SJ 375	Shi	MOS-P-FET-e	VFET, 60/20V, 30A, 60W, <45mΩ, 270/1020ns	(2SK2288) 30p	(TO-220MF)	2SJ280
2 SJ 376	Shi	MOS-P-FET-e	=2SJ375:	(2SK2289) 17c	TO-220 Iso	2SJ295, 2SJ323, 2SJ334
2 SJ 377	Tos	MOS-P-FET-e	VFET, LogL, 60/20V, 5A, 20W, <0,19Ω(2,5A), 45/200ns	30p	TO-251	2SJ192, 2SJ195, 2SJ245, 2SJ279, 2SJ327
2 SJ 378		MOS-P-FET-e	=2SJ377: 1,2W	≈12	-	-
2 SJ 379	Tos	MOS-P-FET-e	VFET, LogL, 100/20V, 8A, 15W, <0,21Ω(4A), 50/110ns	≈30p	-	-
2 SJ 380	Tos	MOS-P-FET-e	VFET, LogL, 100/20V, 12A, 35W, <0,21Ω(6A), 50/110ns	17c	TO-220 Iso	2SJ222
2 SJ 381	Say	MOS-P-FET-e	SMD, VFET, LogL, 12/10V, 2A, on<0,4Ω	39b	SOT-89	2SJ355...356
2 SJ 382	Say	MOS-P-FET-e	VFET, LogL, 12/10V, 4A, 20W, on<177mΩ	30p	TO-251	2SJ192, 2SJ195, 2SJ245, 2SJ279, 2SJ327
2 SJ 383	Say	MOS-P-FET-e	VFET, LogL, 12/10V, 8A, 30W, on<82mΩ	30p	TO-251	2SJ389
2 SJ 384(L,S)	Hit	MOS-P-FET-e*	VFET, LogL, 60/20V, 15/60A, 50W, on<0,1Ω(8A)	30p	(TO-220MF)	2SJ268, 2SJ409
2 SJ 386	Hit	MOS-P-FET-e*	VFET, LogL, 30/20V, 3/5A, 0,9W, <0,4Ω(2A), 36/105ns	7c(9mm)	TO-92L	-
2 SJ 387(L,S)	Hit	MOS-P-FET-e*	VFET, LogL, 20/10V, 10/40A, 20W, on<70mΩ(5A)	30p	TO-251/252	2SJ388...389
2 SJ 388(L,S)	Hit	MOS-P-FET-e*	VFET, LogL, 30/20V, 10/40A, 20W, on<80mΩ(5A)	30p	TO-251/252	2SJ389
2 SJ 389(L,S)	Hit	MOS-P-FET-e*	VFET, LogL, 60/20V, 10/40A, 20W, on<135mΩ(5A)	30p	TO-251/252	-
2 SJ 390	Hit	MOS-P-FET-e*	VFET, LogL, 60/20V, 10/40A, 25W, on<0,12Ω(5A)	17c	SOT-186	2SJ175...176, 2SJ236
2 SJ 399	Hit	MOS-P-FET-e*	SMD, VFET, LogL, 30/20V, 0,2/0,4A, on<7Ω(10mA) 530/7640ns, integr. Rgate	35a	SOT-23	-
2 SJ 400	Say	MOS-P-FET-e	VFET, LogL, 30/20V, 35/140A, 70W, on<35mΩ	30p	(TO-220MF)	2SJ280
2 SJ 403	Say	MOS-P-FET-e	VFET, LogL, 200/20V, 5/20A, 25W, on<1,1Ω	17c	TO-220 Iso	2SJ404...406
2 SJ 404	Say	MOS-P-FET-e	VFET, LogL, 200/20V, 6/24A, 25W, on<0,8Ω	17c	TO-220 Iso	2SJ405...406
2 SJ 405	Say	MOS-P-FET-e	VFET, LogL, 200/20V, 8/32A, 30W, on<0,5Ω	17c	TO-220 Iso	2SJ405
2 SJ 406	Say	MOS-P-FET-e	VFET, LogL, 200/20V, 12/48A, 40W, on<0,23Ω	17c	TO-220 Iso	-
2 SJ 408(L,S)	Hit	MOS-P-FET-e*	VFET, LogL, 60/20V, 50/200A, 100W, on<0,02Ω(25A)	30p	(TO-3FM)	-
2 SJ 409(L,S)	Hit	MOS-P-FET-e*	VFET, LogL, 100/20V, 20/80A, 75W, on<0,16Ω(10A)	30p	(TO-220MF)	(2SJ221) ⁶
2 SJ 410(L,S)	Hit	MOS-P-FET-e*	VFET, 200/20V, 6/24A, 30W, on<0,85Ω(3A), 57/130ns	17c	SOT-186	2SJ307...308
2 SJ 413	Say	MOS-P-FET-e	VFET, LogL, 60/20V, 50/200A, 70W, on<0,02Ω	18c	TO-3P	2SJ218
2 SJ 414	Say	MOS-P-FET-e	VFET, LogL, 60/20V, 15/72A, 50W, on<0,08Ω		(ZP)	-
2 SJ 415	Say	MOS-P-FET-e	VFET, LogL, 60/20V, 8/40A, 40W, on<0,15Ω		(ZP)	-
2 SJ 416	Say	MOS-P-FET-e	SMD, VFET, LogL, 30/20V, 2A, on<0,44Ω	39b	SOT-89	2SJ356
2 SJ 417	Say	MOS-P-FET-e	SMD, VFET, LogL, 30/20V, 4A, 20W, on<0,16Ω	30p	TO-251	2SJ192, 2SJ245, 2SJ279, 2SJ327
2 SJ 418	Say	MOS-P-FET-e	SMD, VFET, LogL, 30/20V, 8A, 30W, on<0,08Ω	30p	TO-251	2SJ467
2 SJ 419	Say	MOS-P-FET-e	SMD, VFET, LogL, 12/10V, 4A, on<82mΩ	8-MDIP	(SOP8)	-
2 SJ 420	Say	MOS-P-FET-e	SMD, VFET, LogL, 12/10V, 5A, on<63mΩ	8-MDIP	(SOP8)	-
2 SJ 421	Say	MOS-P-FET-e	SMD, VFET, LogL, 30/20V, 5A, on<58mΩ	8-MDIP	(SOP8)	-
2 SJ 437	Say	MOS-P-FET-e	VFET, 30/20V, 35/120A, 50W, on<16mΩ		(ZP)	-
2 SJ 454	Say	MOS-P-FET-e	FREDFET, 250/30V, 5/20A, 40W, <1,3Ω		(ZP)	-
2 SJ 455	Say	MOS-P-FET-e	FREDFET, 250/30V, 7/28A, 45W, <0,9Ω		(ZP)	-
2 SJ 456	Say	MOS-P-FET-e	FREDFET, 250/30V, 9/36A, 50W, <0,62Ω		(ZP)	-
2 SJ 457	Say	MOS-P-FET-e	FREDFET, 450/30V, 0,5/2A, 30W, <15Ω	30p	TO-251	-
2 SJ 458	Say	MOS-P-FET-e	FREDFET, 450/30V, 2/8A, 60W, <5,5Ω	30p	(TO-220MF)	-
2 SJ 459	Say	MOS-P-FET-e	FREDFET, 450/30V, 4/16A, 70W, <2,8Ω	30p	(TO-220MF)	-
2 SJ 466	Say	MOS-P-FET-e	VFET, LogL, 30/20V, 35/140A, 50W, on<0,03Ω		(ZP)	-
2 SJ 467	Say	MOS-P-FET-e	VFET, LogL, 30/25V, 8A, 30W, on<0,1Ω	30p	TO-251	2SJ418
2 SJ 468	Say	MOS-P-FET-e	VFET, LogL, 30/25V, 4A, on<0,1Ω	8-MDIP	(SOP8)	-
2 SJ 469	Say	MOS-P-FET-e	VFET, LogL, 30/25V, 5A, on<0,08Ω	8-MDIP	(SOP8)	-

2SK

2 SK 11	Tos	N-FET	Uni, 20V, Idss=0,3...6,5mA, Up=0,5...6V	5n	TO-17	BFS 70, 2N3369, 2N3821, 2SK381, ++
2 SK 12	Tos	N-FET	Uni In, 20V, Idss=0,45...5mA, Up=0,65...4,5V	5n	TO-17	BFS 70, 2N3821, 2N4220, 2SK104, ++
2 SK 13	Tos	N-FET	Uni In, 12V, Idss=0,45...5mA, Up=0,65...4,5V	5n	TO-17	BFS 70, 2N3821, 2N4220, 2SK104, ++
2 SK 15	Tos	N-FET	Uni In, 20V, Idss=0,45...5mA, Up=0,65...5V	5n	TO-17	BFS 70, 2N3821, 2N4220, 2SK104, ++
2 SK 16	Hit	N-FET	Uni In, 15V, Idss=0,5...7mA, Up=0,5...5V	5a	TO-72	BFS 70, 2N3821, 2N4220, 2SK104, ++
2 SK 17	Tos	N-FET	Uni In, 20V, Idss=0,3...6,5mA, Up=0,5...6V	7e	TO-92	BFS 70, 2N3369, 2N3821, 2SK381, ++
2 SK 18	Tos	N-FET	Dual, S,VHF, 40V, Idss=0,45...2,8mA, Up=0,8...3,5V	TO-80	(SGD-DGS-)	-
2 SK 19(TM)	Tos, Mic	N-FET	FM/VHF, 18V, Idss=3...24mA, Up=3>1,2V F<3,5/Gp=20dB(100MHz)	7d (2SK19TM:)	TO-98 TO-92	BF 245 7f BFS 71, BFS 80, BFW 11, 2N3822, 2N4416++
2 SK 22		MOS-N-FET				-
2 SK 23(A)-2...9	Son	N-FET	FM/VHF, 18...40V, Idss=2,7...12mA, Up<4,9V	10a	(BF 245)	7f 2SK107, 2SK192
2 SK 24	Say	N-FET	LFAM, 40V, Idss=0,6...24mA, Up<6V	≈2a	≈TO-18	BF 245 7f BFS 71, 2N3822, 2N4547, 2SK246, 2SK330++
2 SK 25	Say	N-FET	AM/FM, 18V, Idss=0,6...24mA, Up<7,2V F=2,5/Gp=21dB(100MHz)	≈2a	≈TO-18	BF 245 7f BF 244...245, BFS 71, 2N3822...23, ++
2 SK 30(A,ATM)	Tos, Mic	N-FET	LF, Uni, In, 50V, Idss=0,3...6,5mA, Up=0,4...5V	7e	TO-92	BFS 70, 2N3821, 2SK40, 2SK46, 2SK59, ++
2 SK 32	Nec	N-FET	Uni, 35V, 20mA, Idss<10mA, Up<4V	7e	TO-92	BFS 70, 2N3821, 2SK40, 2SK46, 2SK59, ++
2 SK 33	Mit, Mic	N-FET	FM/VHF, 20V, Idss=2,5...20mA, Up=1...8V F=2,5/Gp=20dB(100MHz)	7d	TO-92	BF 245 7f BF 244...245, BFS 71, 2N3822...23, ++
2 SK 34	Mit, Mic	N-FET	LF, Uni, 30V, Idss=0,3...12mA, Up=0,3...6V	7e	TO-92	(BF 245) 7f BFS 70, 2N3369, 2N3821, 2SK381, ++
2 SK 35	Son	N-FET	Uni, 20V, 20mA, Idss<16mA, Up<1,6V	10a		2N5247, 2SK186...187, 2SK363...364, ++